

Phone: (562) 404-4474 \* Fax: (562) 404-1773 ssdi@ssdi-power.com \* www.ssdi-power.com

SDR93

Part Number/Ordering Information <sup>1</sup>

**Designer's Data Sheet** 

L Package Type

Device Type (VRWM)

3 = 300V

4 = 400V

5 = 500V

6 = 600V

/61 = TO-61

<sup>L</sup> Screening <sup>2/</sup>

= Not Screened

TX = TX Level TXV = TXV

S = S Level

# SDR933/61 thru SDR936/61

### 30 Amp **ULTRA FAST RECTIFIER** 300 - 600 Volts 35 nsec

#### FEATURES:

- Ultra Fast Reverse Recovery Time: 35 nsec Max
- Isolated Package
- Reverse Voltage to 600 Volts
- Low Reverse Leakage
- Hermetically Sealed
- Single Chip Construction
- Ultrasonic Aluminum Wire Bonds

- 200°C Operating Temperature

TX, TXV, and S-Level Screening Available<sup>2/</sup>

MAXIMUM RATINGS 3/				
RATING		SYMBOL	VALUE	UNIT
Peak Repetitive Reverse Voltage DC Blocking Voltage (IR = 100μA)	SDR933/61 SDR934/61 SDR935/61 SDR936/61	V <sub>RM(rep)</sub> V <sub>R</sub>	300 400 500 600	Volts
RMS Reverse Voltage	SDR932/61 SDR933/61 SDR934/61 SDR935/61	V <sub>r</sub>	140 210 280 350	Volts
Half Wave Rectified Forward Current, Averaged Over Full Cycle (Resistive Load, 60 Hz, Sine Wave, T <sub>C</sub> = 25°C)		lo	30	Amps
Peak Repetitive Forward Current (T <sub>C</sub> = 55°C, 8.3 ms pulse, allow junction to reach equilibrium between pulses)		I <sub>FM(rep)</sub>	120	Amps
Peak Surge Current (T <sub>C</sub> = 25°C, half sinewave 8.3 ms pulse or equivalent DC)		I <sub>FSM</sub>	300	Amps
Operating & Storage Temperature		T <sub>OP</sub> and T <sub>STG</sub>	-65 to +175	°C
Thermal Resistance	Junction to Case	R <sub>eJC</sub>	1.5	°C/W

#### NOTES:

- 1/ For Ordering Information, Price, and Availability- Contact Factory.
- 2/ Screening Based on MIL-PRF-19500. Screening Flows Available on Request.
- 3/ Unless Otherwise Specified, All Electrical Characteristics @25°C.







SDR933/61 thru SDR936/61

14701 Firestone Blvd \* La Mirada, Ca 90638 Phone: (562) 404-4474 \* Fax: (562) 404-1773 ssdi@ssdi-power.com \* www.ssdi-power.com

CHARACTERISTIC	CS	SYMBOL	MAX	UNIT
Max Instantaneous Forward Voltage Drop ( $I_F = 30 Adc, T_C = 25^{\circ}C, 300 \mu s Pulse$ )		$V_{F2}$	1.7	Vdc
Max Instantaneous Forward Voltage Drop (I <sub>F</sub> = 30Adc, T <sub>C</sub> = 100°C, 300 μs Pulse)		V <sub>F1</sub>	1.5	Vdc
Max Reverse Leakage Current $(T_C = 25^{\circ}C)$	SDR933/61, VR = 300V SDR934/61, VR = 400V SDR935/61, VR = 500V SDR936/61, VR = 600V	I <sub>R1</sub>	100	μAdc
Maximum Reverse Leakage Current (Rated VR, T <sub>C</sub> = 100°C)	SDR933/61, VR = 300V SDR934/61, VR = 400V SDR935/61, VR = 500V SDR936/61, VR = 600V	I <sub>R2</sub>	5.0	mAdc
Max Junction Capacitance $(T_A = 25^{\circ}C, V_R = 10V)$		CJ	250	pf
CHARACTERISTICS	SYMBOL	TYP	MAX	UNIT
Reverse Recovery Time $(I_F = 500\text{mA}, I_R = 1\text{A}, I_{RR} = 250\text{mA})$ $(I_F = 1\text{A to } V_R = 30\text{Vdc})$	t <sub>rr</sub>	30	35	nsec

## Case Outline: 2 Pin TO-61

