

SUPER ORANGE MV873X MV8731 MV8732 MV8733

FEATURES

- Popular T-1 3/4 package
- Super high brightness suitable for outdoor applications
- · Solid state reliability
- · Water clear optics
- · Standard 100 mil. lead spacing



NOTES:

- 1. Dimensions for all drawings are in inches (mm).
- 2. Lead spacing is measured where the leads emerge from the package.
- 3. Protruded resin under the flange is 1.5 mm (0.059") max.

DESCRIPTION

This T-1 3/4 super bright LED has a moderate viewing angle of 30° for concentrated light output. It is made with an AllnGaP LED that emits orange light at 620 nm. It is encapsulated in a water clear epoxy lens package.

ABSOLUTE MAXIMUM RATINGS (T _A = 25°C unless otherwise specified)						
Parameter	Symbol	Rating	Unit			
Operating Temperature	T _{OPR}	-40 to +100	°C			
Storage Temperature	T _{STG}	-40 to +100	°C			
Lead Soldering Time	T _{SOL}	260 for 5 sec	°C			
Continuous Forward Current	I _F	40	mA			
Peak Forward Current		160	mA			
(f = 1.0 KHz, Duty Factor = 1/10)	l le	100				
Reverse Voltage	V _R	5	V			
Power Dissipation	P _D	100	mW			



SUPER ORANGE	MV873X
MV8731 MV8732	
MV8733	

ELECTRICAL / OPTICAL CHARACTERISTICS (TA =25°C)					
Part Number	MV8731	MV8732	MV8733	Condition	
Luminous Intensity (mcd)				$I_F = 20mA$	
Shee 'Minimum	400	630	1000		
Typical	600	940	1500		
Forward Voltage (V)				$I_F = 20mA$	
Maximum	2.8	2.8	2.8		
Typical	2.1	2.1	2.1		
Wavelength (nm)				$I_F = 20mA$	
Peak		620			
Dominant		615			
Spectral Line Half Width (nm)		20		$I_F = 20mA$	
Viewing Angle (°)		20		$I_F = 20mA$	

TYPICAL PERFORMANCE CURVES




Fig. 1 Forward Current vs. Forward Voltage




Fig. 2 Relative Luminous Intensity vs. DC Forward Current

1/27/00 300024A



SUPER ORANGE MV8731 MV8732 MV8733 **MV873X**





Fig. 3 Relative Intensity vs Peak Wavelength



REL. LUMINOUS INTENSITY (%)

Fig. 4 Radiation Diagram




Fig. 5 Current Derating Curve

3 of 4 1/27/00 300024A



DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com

© 2000 Fairchild Semiconductor Corporation