Amplifier Transistors
NPN Silicon

BC182
BC182A
BC182B



CASE 29–11, STYLE 17
TO–92 (TO–226AA)

MAXIMUM RATINGS

Rating	Symbol	BC182	Unit
Collector–Emitter Voltage	V_{CEO}	50	Vdc
Collector–Base Voltage	V_{CBO}	60	Vdc
Emitter–Base Voltage	V_{EBO}	6.0	Vdc
Collector Current — Continuous	I_C	100	mAdc
Total Device Dissipation @ T_A = 25°C Derate above 25°C	P_D	350 2.8	mW mW/°C
Total Device Dissipation @ T_C = 25°C Derate above 25°C	P_D	1.0 8.0	Watts mW/°C
Operating and Storage Junction Temperature Range	T_J, T_{stg}	–55 to +150	°C

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Ambient	$R_{\theta JA}$	357	°C/W
Thermal Resistance, Junction to Case	$R_{\theta JC}$	125	°C/W



ELECTRICAL CHARACTERISTICS (T_A = 25°C unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
OFF CHARACTERISTICS					
Collector–Emitter Breakdown Voltage (I_C = 2.0 mA, I_B = 0)	$V_{(BR)CEO}$	50	—	—	V
Collector–Base Breakdown Voltage (I_C = 10 μA, I_E = 0)	$V_{(BR)CBO}$	60	—	—	V
Emitter–Base Breakdown Voltage (I_E = 100 μA, I_C = 0)	$V_{(BR)EBO}$	6.0	—	—	V
Collector Cutoff Current (V_{CB} = 50 V, V_{BE} = 0)	I_{CBO}	—	0.2	15	nA
Emitter–Base Leakage Current (V_{EB} = 4.0 V, I_C = 0)	I_{EBO}	—	—	15	nA

May, 2001 – Rev. 2
Publication Order Number:
BC182/D

ELECTRICAL CHARACTERISTICS (T_A = 25°C unless otherwise noted) (Continued)

Characteristic		Symbol	Min	Typ	Max	Unit
ON CHARACTERISTICS						
DC Current Gain		h_{FE}				—
(I_C = 10 μA, V_{CE} = 5.0 V)	BC182		40	—	—	
(I_C = 2.0 mA, V_{CE} = 5.0 V)	BC182		120	—	500	
	BC182A		120		220	
	BC182B		180	—	500	
(I_C = 100 mA, V_{CE} = 5.0 V)	BC182		80		—	
Collector–Emitter On Voltage		$V_{CE(sat)}$				V
(I_C = 10 mA, I_B = 0.5 mA)			—	0.07	0.25	
(I_C = 100 mA, I_B = 5.0 mA)(1)			—	0.2	0.6	
Base–Emitter Saturation Voltage (I_C = 100 mA, I_B = 5.0 mA)(1)		$V_{BE(sat)}$	—	—	1.2	V
Base–Emitter On Voltage		$V_{BE(on)}$				V
(I_C = 100 μA, V_{CE} = 5.0 V)			—	0.5	—	
(I_C = 2.0 mA, V_{CE} = 5.0 V)			0.55	0.62	0.7	
(I_C = 100 mA, V_{CE} = 5.0 V)(1)			—	0.83	—	
DYNAMIC CHARACTERISTICS						
Current–Gain — Bandwidth Product		f_T				MHz
(I_C = 0.5 mA, V_{CE} = 3.0 V, f = 100 MHz)			—	100	—	
(I_C = 10 mA, V_{CE} = 5.0 V, f = 100 MHz)			150	200	—	
Common Base Output Capacitance (V_{CB} = 10 V, I_C = 0, f = 1.0 MHz)		C_{ob}	—	—	5.0	pF
Common Base Input Capacitance (V_{EB} = 0.5 V, I_C = 0, f = 1.0 MHz)		C_{ib}	—	8.0	—	pF
Small–Signal Current Gain		h_{fe}				—
(I_C = 2.0 mA, V_{CE} = 5.0 V, f = 1.0 kHz)	BC182		125	—	500	
	BC182A		125	—	260	
	BC182B		240	—	500	
Noise Figure (I_C = 0.2 mA, V_{CE} = 5.0 V, R_S = 2.0 kΩ, f = 1.0 kHz)		NF	—	2.0	10	dB

1. Pulse Test: Tp 300 s, Duty Cycle 2.0%.



Figure 1. Normalized DC Current Gain



Figure 1. “Saturation” and “On” Voltages



Figure 2. Current–Gain — Bandwidth Product



Figure 3. Capacitances



Figure 4. Base Spreading Resistance

PACKAGE DIMENSIONS

BC182

TO–92 (TO–226)
CASE 29–11
ISSUE AL





SECTION X–X

NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: INCH.
3. CONTOUR OF PACKAGE BEYOND DIMENSION R IS UNCONTROLLED.
4. LEAD DIMENSION IS UNCONTROLLED IN P AND BEYOND DIMENSION K MINIMUM.

	INCHES		MILLIMETERS	
DIM	MIN	MAX	MIN	MAX
A	0.175	0.205	4.45	5.20
B	0.170	0.210	4.32	5.33
C	0.125	0.165	3.18	4.19
D	0.016	0.021	0.407	0.533
G	0.045	0.055	1.15	1.39
H	0.095	0.105	2.42	2.66
J	0.015	0.020	0.39	0.50
K	0.500	---	12.70	---
L	0.250	---	6.35	---
N	0.080	0.105	2.04	2.66
P	---	0.100	---	2.54
R	0.115	---	2.93	---
V	0.135	---	3.43	---

TYLE 17:
PIN 1. COLLECTOR
2. BASE
3. EMITTER

PUBLICATION ORDERING INFORMATION

Literature Fulfillment:
Literature Distribution Center for ON Semiconductor
P.O. Box 5163, Denver, Colorado 80217 USA
Phone: 303–675–2175 or 800–344–3860 Toll Free USA/Canada
Fax: 303–675–2176 or 800–344–3867 Toll Free USA/Canada
Email: ONlit@hibbertco.com

N. American Technical Support: 800–282–9855 Toll Free USA/Canada

JAPAN: ON Semiconductor, Japan Customer Focus Center
4–32–1 Nishi–Gotanda, Shinagawa–ku, Tokyo, Japan 141–0031
Phone: 81–3–5740–2700
Email: r14525@onsemi.com

ON Semiconductor Website: http://onsemi.com

For additional information, please contact your local Sales Representative.