


# Zener Diodes

## ●RLZ Series (Pd=400mW Package : LL-34)

Series Prefix	Nominal Zener voltage	Vz (V)				Iz (mA)	Zz (Ω) Max.	Iz (mA)	Zzk (Ω) Max.	Iz (mA)	IR (μA) Max.	VR (V)
		Ranking										
		A	B	C	D							
RLZ	2.0	1.880~2.100	2.020~2.200	-	-	20	140	20	2000	1	120	0.5
RLZ	2.2	2.120~2.300	2.220~2.410	-	-	20	120	20	2000	1	120	0.7
RLZ	2.4	2.330~2.520	2.430~2.830	-	-	20	100	20	2000	1	120	1.0
RLZ	2.7	2.540~2.750	2.690~2.910	-	-	20	100	20	1000	1	100	1.0
RLZ	3.0	2.850~3.070	3.010~3.220	-	-	20	80	20	1000	1	50	1.0
RLZ	3.3	3.160~3.380	3.320~3.530	-	-	20	70	20	1000	1	20	1.0
RLZ	3.6	3.455~3.695	3.600~3.845	-	-	20	60	20	1000	1	10	1.0
RLZ	3.9	3.74~4.01	3.89~4.16	-	-	20	50	20	1000	1	5	1.0
RLZ	4.3	4.04~4.29	4.17~4.43	4.30~4.57	-	20	40	20	1000	1	5	1.0
RLZ	4.7	4.44~4.68	4.55~4.80	4.68~4.93	-	20	25	20	900	1	5	1.0
RLZ	5.1	4.81~5.07	4.94~5.20	5.09~5.37	-	20	20	20	800	1	5	1.5
RLZ	5.6	5.28~5.55	5.45~5.73	5.61~5.91	-	20	13	20	500	1	5	2.5
RLZ	6.2	5.78~6.09	5.96~6.27	6.12~6.44	-	20	10	20	300	1	5	3.0
RLZ	6.8	6.29~6.63	6.49~6.83	6.66~7.01	-	20	8	20	150	0.5	2	3.5
RLZ	7.5	6.85~7.22	7.07~7.45	7.29~7.67	-	20	8	20	120	0.5	0.5	4.0
RLZ	8.2	7.53~7.92	7.78~8.19	8.03~8.45	-	20	8	20	120	0.5	0.5	5.0
RLZ	9.1	8.29~8.73	8.57~9.01	8.83~9.30	-	20	8	20	120	0.5	0.5	6.0
RLZ	10	9.12~9.59	9.41~9.90	9.70~10.20	9.94~10.44	20	8	20	120	0.5	0.2	7.0
RLZ	11	10.18~10.71	10.50~11.05	10.82~11.38	-	10	10	10	120	0.5	0.2	8.0
RLZ	12	11.13~11.71	11.44~12.03	11.74~12.35	-	10	12	10	110	0.5	0.2	9.0
RLZ	13	12.11~12.75	12.55~13.21	12.99~13.68	-	10	14	10	110	0.5	0.2	10
RLZ	15	13.44~14.13	13.89~14.62	14.35~15.09	-	10	16	10	110	0.5	0.2	11
RLZ	16	14.80~15.57	15.25~16.04	15.69~16.51	-	10	18	10	150	0.5	0.2	12
RLZ	18	16.22~17.06	16.82~17.70	17.42~18.33	-	10	23	10	150	0.5	0.2	13
RLZ	20	18.02~18.96	18.63~19.59	19.23~20.22	19.72~20.72	10	28	10	200	0.5	0.2	15
RLZ	22	20.15~21.20	20.64~21.71	21.08~22.17	21.52~22.63	5	30	5	200	0.5	0.2	17
RLZ	24	22.05~23.18	22.61~23.77	23.12~24.31	23.63~24.85	5	35	5	200	0.5	0.2	19
RLZ	27	24.26~25.52	24.97~26.26	25.63~26.95	26.29~27.64	5	45	5	250	0.5	0.2	21
RLZ	30	26.99~28.39	27.70~29.13	28.36~29.82	29.02~30.51	5	55	5	250	0.5	0.2	23
RLZ	33	29.68~31.22	30.32~31.88	30.90~32.50	31.49~33.11	5	65	5	250	0.5	0.2	25
RLZ	36	32.14~33.79	32.79~34.49	33.40~35.13	34.01~35.77	5	75	5	250	0.5	0.2	27
RLZ	39	34.68~36.47	35.36~37.19	36.00~37.85	36.63~38.52	5	85	5	250	0.5	0.2	30
RLZ	39E		37.36~39.29			5	85	5	250	0.5	0.2	30
RLZ	39F		38.14~40.11			5	85	5	250	0.5	0.2	30
RLZ	39G		38.94~40.80			5	85	5	250	0.5	0.2	30
New RLZ	43		40.00~45.00			5	90	5	-	-	0.2	33
New RLZ	47		44.00~49.00			5	90	5	-	-	0.2	36
New RLZ	51		48.00~54.00			5	110	5	-	-	0.2	39
New RLZ	56		53.00~60.00			5	110	5	-	-	0.2	43

Notes : 1. Zener voltage (Vz) is measured 40ms after supplying current.  
 2. When ordering, specify the rank of the diodes. Otherwise, the diodes of rank A, B or C are supplied.

(Unit : mm)



### ●Product Designation

- When ordering, specify the type.
- Check each code against the tables shown below.
- Fill a space with the next character.

**R L Z T E - 1 1 2 . 0 A**

Series Prefix

RLZ Series

Packaging

Package	Code	Sprocket hole side	Quantity/Package (pcs)
LL-34	TE-11	Cathode	2,500
	TE-12	Anode	

Nominal Zener voltage

Ranking