


DS1743/DS1743P Y2K-Compliant, Nonvolatile Timekeeping RAMs

www.maxim-ic.com

FEATURES

- Integrated NV SRAM, Real-Time Clock, Crystal, Power-Fail Control Circuit, and Lithium Energy Source
- Clock Registers are Accessed Identically to the Static RAM. These Registers Reside in the Eight Top RAM Locations.
- Century Byte Register
- Totally Nonvolatile with Over 10 Years of Operation in the Absence of Power
- BCD-Coded Century, Year, Month, Date, Day, Hours, Minutes, and Seconds with Automatic Leap Year Compensation Valid through 2099
- Low-Battery-Voltage Level Indicator Flag
- Power-Fail Write Protection Allows for ±10%
 V_{CC} Power-Supply Tolerance
- Lithium Energy Source is Electrically Disconnected to Retain Freshness Until Power is Applied for the First Time
- DIP Module Only Standard JEDEC Bytewide 8k x 8 Static RAM Pinout
- PowerCap Module Board Only
 Surface-Mountable Package for Direct
 Connection to PowerCap Containing
 Battery and Crystal
 Replaceable Battery (PowerCap)
 Power-On Reset Output
 Pin-for-Pin Compatible with Other Densities
 of DS174XP Timekeeping RAM
- Underwriters Laboratory (UL) Recognized to Prevent Charging of the Internal Lithium Battery

PIN CONFIGURATIONS



Note: Some revisions of this device may incorporate deviations from published specifications known as errata. Multiple revisions of any device may be simultaneously available through various sales channels. For information about device errata, click here: www.maxim-ic.com/errata.

1 of 16 REV: 121306

PIN DESCRIPTION

I III DL	FIN DESCRIPTION									
P	IN	NAME	EUNCTION							
PDIP	PowerCap	NAME	FUNCTION							
1	1, 2, 3, 31–34	N.C.	No Connection							
2	30	A12								
3	25	A7								
4	24	A6								
5	23	A5								
6	22	A4	Address Input							
7	21	A3								
8	20	A2								
9	19	A1								
10	18	A0								
11	16	DQ0	Data Innest/							
12	15	DQ1	Data Input/ Output							
13	14	DQ2	Output							
14	17	GND	Ground							
15	13	DQ3								
16	12	DQ4	Data Innest/							
17	11	DQ5	Data Input/ Output							
18	10	DQ6	Output							
19	9	DQ7								

F	PIN	NAME	FUNCTION
PDIP	PowerCap		
20	8	CE	Chip Enable, Active Low
21	28	A10	Address Input
22	7	ŌĒ	Output Enable, Active Low
23	29	A11	Address Input
24	27	A9	
25	26	A8	
26		CE2	Chip Enable 2
27	6	WE	Write Enable, Active Low
28	5	V _{CC}	Power-Supply Input
_	4	RST	Power-On Reset Output, Active Low
_		X1, X2	Crystal Connection
_		V_{BAT}	Battery Connection

ORDERING INFORMATION

PART	TEMP RANGE	PIN-PACKAGE	VOLTAGE (V)	TOP MARK**
DS1743 -70	0° C to $+70^{\circ}$ C	28 EDIP Module	5	DS1743-70
DS1743-85	0° C to $+70^{\circ}$ C	28 EDIP Module	5	DS1743-85
DS1743-100	0° C to $+70^{\circ}$ C	28 EDIP Module	5	DS1743-100
DS1743-100 IND	-40°C to +85°C	28 EDIP Module	5	DS1743-100-IND
DS1743P-70	0° C to $+70^{\circ}$ C	34 PowerCap*	5	DS1743P-70
DS1743P-85	0° C to $+70^{\circ}$ C	34 PowerCap*	5	DS1743P-85
DS1743P-100	0°C to +70°C	34 PowerCap*	5	DS1743P-100
DS1743P-100IND	-40°C to +85°C	34 PowerCap*	5	DS1743P-100 IND
DS1743W-120	0°C to +70°C	28 EDIP Module	3.3	DS1743W-120
DS1743W-120 IND	-40°C to +85°C	28 EDIP Module	3.3	DS1743W-120 IND
DS1743W-150	0°C to +70°C	28 EDIP Module	3.3	DS1743W-150
DS1743W-150 IND	-40°C to +85°C	28 EDIP Module	3.3	DS1743W-150 IND
DS1743WP-120	0°C to +70°C	34 PowerCap*	3.3	DS1743WP-120
DS1743WP-120 IND	-40°C to +85°C	34 PowerCap*	3.3	DS1743WP-120 IND
DS1743-70+	0°C to +70°C	28 EDIP Module	5	DS1743-70
DS1743-85+	0°C to +70°C	28 EDIP Module	5	DS1743-85
DS1743-100+	0° C to $+70^{\circ}$ C	28 EDIP Module	5	DS1743-100
DS1743-100 IND+	-40°C to +85°C	28 EDIP Module	5	DS1743-100-IND
DS1743P-70+	0° C to $+70^{\circ}$ C	34 PowerCap*	5	DS1743P-70
DS1743P-85+	0° C to $+70^{\circ}$ C	34 PowerCap*	5	DS1743P-85
DS1743P-100+	0° C to $+70^{\circ}$ C	34 PowerCap*	5	DS1743P-100
DS1743P-100IND+	-40°C to +85°C	34 PowerCap*	5	DS1743P-100 IND
DS1743W-120+	0° C to $+70^{\circ}$ C	28 EDIP Module	3.3	DS1743W-120
DS1743W-120 IND+	-40°C to +85°C	28 EDIP Module	3.3	DS1743W-120 IND
DS1743W-150+	0°C to +70°C	28 EDIP Module	3.3	DS1743W-150
DS1743W-150 IND+	-40°C to +85°C	28 EDIP Module	3.3	DS1743W-150 IND
DS1743WP-120+	0°C to +70°C	34 PowerCap*	3.3	DS1743WP-120
DS1743WP-120 IND+	-40°C to +85°C	34 PowerCap*	3.3	DS1743WP-120 IND
DS9034PCX	0°C to +70°C	PowerCap	_	DS9034PC
DS90340I-PCX	-40°C to +85°C	PowerCap IND	_	DS9034PCI
DS9034PCX+	0°C to +70°C	PowerCap		DS9034PC
DS90340I-PCX+	-40°C to +85°C	PowerCap IND		DS9034PCI

^{*}DS9034PCX required (must be ordered separately).

DESCRIPTION

The DS1743 is a full-function, year-2000-compliant (Y2KC), real-time clock/calendar (RTC) and 8k x 8 nonvolatile static RAM. User access to all registers within the DS1743 is accomplished with a bytewide interface as shown in Figure 1. The RTC information and control bits reside in the eight uppermost RAM locations. The RTC registers contain century, year, month, date, day, hours, minutes, and seconds data in 24-hour binary-coded decimal (BCD) format. Corrections for the day of the month and leap year are made automatically. The RTC clock registers are double buffered to avoid access of incorrect data that can occur during clock update cycles. The double-buffered system also prevents time loss as the timekeeping countdown continues unabated by access to time register data. The DS1743 also contains its own powerfail circuitry, which deselects the device when the V_{CC} supply is in an out-of-tolerance condition. When V_{CC} is above V_{PF} , the device is fully accessible. When V_{CC} is below V_{PF} , the internal \overline{CE} signal is forced

^{**}A '+' indicates lead-free. The top mark will include a '+' symbol on lead-free devices.

high, preventing any access. When V_{CC} rises above V_{PF} , access remains inhibited for T_{REC} , allowing time for the system to stabilize. These features prevent loss of data from unpredictable system operation brought on by low V_{CC} as errant access and update cycles are avoided.

PACKAGES

The DS1743 is available in two packages: the 28-pin DIP and the 34-pin PowerCap module. The 28-pin DIP-style module integrates the crystal, lithium energy source, and silicon all in one package. The 34-pin PowerCap Module Board is designed with contacts for connection to a separate PowerCap (DS9034PCX) that contains the crystal and battery. This design allows the PowerCap to be mounted on top of the DS1743P after the completion of the surface-mount process. Mounting the PowerCap after the surface-mount process prevents damage to the crystal and battery due to the high temperatures required for solder reflow. The PowerCap is keyed to prevent reverse insertion. The PowerCap Module Board and PowerCap are ordered separately and shipped in separate containers. The part number for the PowerCap is DS9034PCX.

TIME AND DATE OPERATION

The time and date information is obtained by reading the appropriate register bytes. Table 2 shows the RTC registers. The time and date are set or initialized by writing the appropriate register bytes. The contents of the time and date registers are in the BCD format. The day-of-week register increments at midnight. Values that correspond to the day of week are user-defined, but must be sequential (i.e., if 1 equals Sunday, then 2 equals Monday and so on). Illogical time and date entries result in undefined operation.

CLOCK OPERATIONS-READING THE CLOCK

While the double-buffered register structure reduces the chance of reading incorrect data, internal updates to the DS1743 clock registers should be halted before clock data is read to prevent reading of data in transition. However, halting the internal clock register updating process does not affect clock accuracy. Updating is halted when a 1 is written into the read bit, bit 6 of the century register (see Table 2). As long as a 1 remains in that position, updating is halted. After a halt is issued, the registers reflect the count that is day, date, and time that was current at the moment the halt command was issued. However, the internal clock registers of the double-buffered system continue to update so that the clock accuracy is not affected by the access of data. All the DS1743 registers are updated simultaneously after the internal clock register updating process has been re-enabled. Updating is within a second after the read bit is written to 0.

The READ bit must be a zero for a minimum of 500µs to ensure the external registers are updated.

Figure 1. Block Diagram




Table 1. Truth Table

V _{CC}	C E	CE2	ŌĒ	WE	MODE	DQ	POWER
	$V_{ m IH}$	X	X	X	Deselect	High-Z	Standby
	X	$V_{\rm IL}$	X	X	Deselect	High-Z	Standby
$V_{CC} > V_{PF}$	$V_{\rm IL}$	V_{IH}	X	$V_{\rm IL}$	Write	Data In	Active
	$V_{\rm IL}$	V_{IH}	V_{IL}	V_{IH}	Read	Data Out	Active
	$V_{\rm IL}$	V_{IH}	V_{IH}	V_{IH}	Read	High-Z	Active
$V_{SO} < V_{CC} < V_{PF}$	X	X	X	X	Deselect	High-Z	CMOS Standby
$V_{CC} < V_{SO} < V_{PF}$	X	X	X	X	Deselect	High-Z	Data-Retention Mode

SETTING THE CLOCK

As shown in Table 2, bit 7 of the century register is the write bit. Setting the write bit to a 1, like the read bit, halts updates to the DS1743 registers. The user can then load them with the correct day, date and time data in 24-hour BCD format. Resetting the write bit to a 0 then transfers those values to the actual clock counters and allows normal operation to resume.

STOPPING AND STARTING THE CLOCK OSCILLATOR

The clock oscillator may be stopped at any time. To increase the shelf life, the oscillator can be turned off to minimize current drain from the battery. The \overline{OSC} bit is the MSB (bit 7) of the seconds registers, see Table 2. Setting it to a 1 stops the oscillator.

FREQUENCY TEST BIT

As shown in Table 2, bit 6 of the day byte is the frequency test bit. When the frequency test bit is set to logic 1 and the oscillator is running, the LSB of the seconds register will toggle at 512Hz. When the seconds register is being read, the $\overline{DQ0}$ line will toggle at the 512Hz frequency as long as conditions for access remain valid (i.e., \overline{CE} low, \overline{OE} low, \overline{WE} high, and address for seconds register remain valid and stable).

CLOCK ACCURACY (DIP MODULE)

The DS1743 is guaranteed to keep time accuracy to within ±1 minute per month at +25°C. The RTC is calibrated at the factory by Dallas Semiconductor using nonvolatile tuning elements, and does not require additional calibration. For this reason, methods of field clock calibration are not available and not necessary. The electrical environment also affects clock accuracy, so caution should be taken to place the RTC in the lowest-level EMI section of the PC board layout. For additional information, please refer to Application Note 58: Crystal Considerations with Dallas Real-Time Clocks.

CLOCK ACCURACY (PowerCap MODULE)

The DS1743 and DS9034PCX are each individually tested for accuracy. Once mounted together, the module will typically keep time accuracy to within ± 1.53 minutes per month (35ppm) at ± 25 °C. The electrical environment also affects clock accuracy, so caution should be taken to place the RTC in the lowest-level EMI section of the PC board layout. For additional information, please refer to *Application Note 58: Crystal Considerations with Dallas Real-Time Clocks*.

Table 2. Register Map

. 45.0 2.110	9.0.0.									
ADDRESS				DATA	4				FUNCTION	RANGE
ADDRESS	B ₇	\mathbf{B}_{6}	B ₅	$\mathbf{B_4}$	$\mathbf{B_3}$	$\mathbf{B_2}$	\mathbf{B}_1	$\mathbf{B_0}$	FUNCTION	KANGE
1FFF		10	Year			Year	ſ		Year	00–99
1FFE	X	X	X	10 Month	Month				Month	01–12
1FFD	X	X	10 1	Date		Date	•		Date	01–31
1FFC	BF	FT	X	X	X		Day		Day	01–07
1FFB	X	X	10 I	Hour		Hou	r		Hour	00–23
1FFA	X		10 Minute	es	Minutes				Minutes	00–59
1FF9	OSC	-	10 Second	ds	Seconds				Seconds	00–59
1FF8	W	R	10 Ce	entury		Centu	ry		Control	00–39

OSC = STOP BIT

R = READ BIT

FT = FREQUENCY TEST

W = WRITE BIT X = SEE NOTE BELOW

BF = BATTERY FLAG

Note: All indicated "X" bits must be set to "0" when written to ensure proper clock operation.

RETRIEVING DATA FROM RAM OR CLOCK

The DS1743 is in the read mode whenever \overline{OE} (output enable) is low, \overline{WE} (write enable) is high, and \overline{CE} (chip enable) is low. The device architecture allows ripple-through access to any of the address locations in the NV SRAM. Valid data will be available at the DQ pins within t_{AA} after the last address input is stable, providing that the, \overline{CE} and \overline{OE} access times and states are satisfied. If \overline{CE} , or \overline{OE} access times and states are not met, valid data will be available at the latter of chip enable access (t_{CEA}) or at output enable access time (t_{CEA}). The state of the data input/output pins (DQ) is controlled by \overline{CE} and \overline{OE} . If the outputs are activated before t_{AA} , the data lines are driven to an intermediate state until t_{AA} . If the address inputs are changed while \overline{CE} and \overline{OE} remain valid, output data will remain valid for output data hold time (t_{OH}) but will then go indeterminate until the next address access.

WRITING DATA TO RAM OR CLOCK

The DS1743 is in the write mode whenever \overline{WE} , and \overline{CE} are in their active state. The start of a write is referenced to the latter occurring transition of \overline{WE} , on \overline{CE} . The addresses must be held valid throughout the cycle. \overline{CE} or \overline{WE} must return inactive for a minimum of t_{WR} prior to the initiation of another read or write cycle. Data in must be valid t_{DS} prior to the end of write and remain valid for t_{DH} afterward. In a typical application, the \overline{OE} signal will be high during a write cycle. However, \overline{OE} can be active provided that care is taken with the data bus to avoid bus contention. If \overline{OE} is low prior to \overline{WE} transitioning low the data bus can become active with read data defined by the address inputs. A low transition on \overline{WE} will then disable the outputs t_{WEZ} after \overline{WE} goes active.

DATA-RETENTION MODE

The 5V device is fully accessible and data can be written or read only when V_{CC} is greater than V_{PF} . However, when V_{CC} is below the power-fail point, V_{PF} , (point at which write protection occurs) the internal clock registers and SRAM are blocked from any access. At this time (PowerCap only) the powerfail reset-output signal (\overline{RST}) is driven active and remains active until V_{CC} returns to nominal levels. When V_{CC} falls below the battery switch point V_{SO} (battery supply level), device power is switched from the V_{CC} in to the backup battery. RTC operation and SRAM data are maintained from the battery until V_{CC} is returned to nominal levels.

The 3.3V device is fully accessible and data can be written or read only when V_{CC} is greater than V_{PF} . When V_{CC} falls below the power-fail point, V_{PF} , access to the device is inhibited. At this time the power-fail reset-output signal (\overline{RST}) is driven active and remains active until V_{CC} returns to nominal levels. If V_{PF} is less than V_{SO} , the device power is switched from V_{CC} to the backup supply (V_{BAT}) when V_{CC} drops below V_{PF} . If V_{PF} is greater than V_{SO} , the device power is switched from V_{CC} to the backup supply (V_{BAT}) when V_{CC} drops below V_{SO} . RTC operation and SRAM data are maintained from the battery until V_{CC} is returned to nominal levels. The \overline{RST} (PowerCap only) signal is an open-drain output and requires a pullup resistor. Except for \overline{RST} , all control, data, and address signals must be powered down when V_{CC} is powered down.

BATTERY LONGEVITY

The DS1743 has a lithium power source that is designed to provide energy for clock activity and clock and RAM data retention when the V_{CC} supply is not present. The capability of this internal power supply is sufficient to power the DS1743 continuously for the life of the equipment in which it is installed. For specification purposes, the life expectancy is 10 years at +25°C with the internal clock oscillator running in the absence of V_{CC} power. Each DS1743 is shipped from Dallas Semiconductor with its lithium energy source disconnected, guaranteeing full energy capacity. When V_{CC} is first applied at a level greater than V_{PF} , the lithium energy source is enabled for battery backup operation. Actual life expectancy of the DS1743 will be longer than 10 years since no lithium battery energy is consumed when V_{CC} is present.

BATTERY MONITOR

The DS1743 constantly monitors the battery voltage of the internal battery. The battery flag bit (bit 7) of the day register is used to indicate the voltage level range of the battery. This bit is not writeable and should always be a 1 when read. If a 0 is ever present, an exhausted lithium energy source is indicated and both the contents of the RTC and RAM are questionable.

ABSOLUTE MAXIMUM RATINGS

Voltage Range on Any Pin Relative to Ground	0.3V to +6.0V
Operating Temperature Range	40°C to +85°C
Storage Temperature Range	
Soldering Temperature (EDIP) (leads, 10 seconds)	
Soldering Temperature	

This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operation sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods of time may affect device reliability.

OPERATING RANGE

RANGE	TEMP RANGE	$ m V_{CC}$
Commercial	0°C to +70°C	$3.3V \pm 10\%$ or $5V \pm 10\%$
Industrial	-40°C to +85°C	$3.3V \pm 10\%$ or $5V \pm 10\%$

RECOMMENDED DC OPERATING CONDITIONS

 $(T_A = Over the Operating Range.)$

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS	NOTES
Logic 1 Voltage All Inputs	V	$V_{CC} = 5V \pm 10\%$	2.2		V _{CC} +0.3V	V	1
	$ m V_{IH}$	$V_{CC} = 3.3V$ ±10%	2.0		V _{CC} +0.3V	V	1
	$ m V_{IL}$	$V_{CC} = 5V \pm 10\%$	-0.3		+0.8	V	1
Logic 0 Voltage All Inputs		$V_{CC} = 3.3V$ $\pm 10\%$	-0.3		+0.6	V	1

DC ELECTRICAL CHARACTERISTICS (5V)

($V_{CC} = 5.0V \pm 10\%$, $T_A = Over the Operating Range.$)

PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Active Supply Current	I_{CC}		15	50	mA	2, 3
TTL Standby Current $(\overline{CE} = V_{IH}, CE2 = V_{IL})$	I _{CC1}		1	3	mA	2, 3
CMOS Standby Current $(\overline{CE} \ge V_{CC} - 0.2V; CE2 = GND + 0.2V)$	I_{CC2}		1	3	mA	2, 3
Input Leakage Current (Any Input)	${ m I}_{ m IL}$	-1		+1	μΑ	
Output Leakage Current (Any Output)	I_{OL}	-1		+1	μΑ	
Output Logic 1 Voltage (I _{OUT} = -1.0mA)	$V_{ m OH}$	2.4				1
Output Logic 0 Voltage (I _{OUT} = 2.1mA)	V_{OL1}			0.4		1
Write-Protection Voltage	$V_{ m PF}$	4.20		4.50	V	1
Battery Switchover Voltage	V_{SO}		V_{BAT}			1, 4

DC ELECTRICAL CHARACTERISTICS (3.3V)

(V_{CC} = 3.3V ±10%, T_A = Over the Operating Range.)

PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Active Supply Current	I_{CC}		10	30	mA	2, 3
TTL Standby Current ($\overline{CE} = V_{IH}$)	I_{CC1}		0.7	2	mA	2, 3
CMOS Standby Current $(\overline{CE} \ge V_{CC} - 0.2V;$ CE2 = GND + 0.2V)	I_{CC2}		0.7	2	mA	2, 3
Input Leakage Current (Any Input)	I_{IL}	-1		+1	μΑ	
Output Leakage Current (Any Output)	I_{OL}	-1		+1	μΑ	
Output Logic 1 Voltage (I _{OUT} = -1.0mA)	V_{OH}	2.4				1
Output Logic 0 Voltage (I _{OUT} =2.1mA)	V_{OL1}			0.4		1
Write-Protection Voltage	V_{PF}	2.75		2.97	V	1
Battery Switchover Voltage	V_{SO}		$egin{array}{c} V_{BAT} \ or \ V_{PF} \end{array}$		V	1, 4

AC CHARACTERISTICS—READ CYCLE (5V)

 $(V_{CC} = 5.0V \pm 10\%, T_A = Over the Operating Range.)$


				AC	CESS				
PARAMETER	SYMBOL	70ns		85ns		100ns		UNITS	NOTES
		MIN	MAX	MIN	MAX	MIN	MAX		
Read Cycle Time	t_{RC}	70		85		100		ns	
Address Access Time	t_{AA}		70		85		100	ns	
TE to CE2 to DQ Low-Z	$t_{ m CEL}$	5		5		5		ns	5
CE Access Time	t_{CEA}		70		85		100	ns	5
CE2 Access Time	t_{CE2A}		80		95		105	ns	5
CE and CE2 Data-Off Time	t_{CEZ}		25		30		35	ns	
OE to DQ Low-Z	$t_{ m OEL}$	5		5		5		ns	
OE Access Time	t_{OEA}		35		45		55	ns	
OE Data-Off Time	t _{OEZ}		25		30		35	ns	
Output Hold from Address	t _{OH}	5		5		5		ns	

AC CHARACTERISTICS—READ CYCLE (3.3V)

(V_{CC} = 3.3V ±10%, T_A = Over the Operating Range.)

			ACC				
PARAMETER	SYMBOL	12	0ns	150ns		UNITS	NOTES
		MIN	MAX	MIN	MAX		
Read Cycle Time	t_{RC}	120		150		ns	
Address Access Time	t_{AA}		120		150	ns	
CE and CE2 Low to DQ Low-Z	$t_{ m CEL}$	5		5		ns	5
CE and CE2 Access Time	$t_{\rm CEA}$		120		150	ns	5
CE and CE2 Data-Off time	t_{CEZ}		40		50	ns	5
OE Low to DQ Low-Z	$t_{ m OEL}$	5		5		ns	
OE Access Time	$t_{ m OEA}$		100		130	ns	
OE Data-Off Time	t _{OEZ}		35		35	ns	
Output Hold from Address	t _{OH}	5		5		ns	

READ CYCLE TIMING DIAGRAM



AC CHARACTERISTICS—WRITE CYCLE (5V)

(V_{CC} = 5.0V ±10%, T_A = Over the Operating Range.)


				AC	CESS				
PARAMETER	SYMBOL	70ns		85ns		100ns		UNITS	NOTES
		MIN	MAX	MIN	MAX	MIN	MAX		
Write Cycle Time	$t_{ m WC}$	70		85		100		ns	
Address Setup Time	t _{AS}	0		0		0		ns	5
WE Pulse Width	$t_{ m WEW}$	50		65		70		ns	
CE Pulse Width	t_{CEW}	60		70		75		ns	5
CE2 Pulse Width	$t_{\rm CE2W}$	65		75		85		ns	5
Data Setup Time	$t_{ m DS}$	30		35		40		ns	5
Data Hold Time CE	t_{DH}	0		0		0		ns	5
Data Hold Time CE2	t_{DH}	8		8		8		ns	5
Address Hold Time	$t_{ m AH}$	5		5		5		ns	5
WE Data-Off Time	$t_{ m WEZ}$		25		30		35	ns	
Write Recovery Time	$t_{ m WR}$	10		10		10		ns	

AC CHARACTERISTICS—WRITE CYCLE (3.3V)


(V_{cc} = 3.3V ±10%, T_A = Over the Operating Range.)

		ACCESS					
PARAMETER	SYMBOL	120ns		150ns		UNITS	NOTES
		MIN	MAX	MIN	MAX		
Write Cycle Time	$t_{ m WC}$	120		150		ns	
Address Setup Time	t_{AS}	0		0		ns	5
WE Pulse Width	$t_{ m WEW}$	100		130		ns	
CE and CE2 Pulse Width	t_{CEW}	110		140		ns	5
Data Setup Time	$t_{ m DS}$	80		90		ns	5
Data Hold Time CE	$t_{ m DH}$	0		0		ns	5
Data Hold Time CE2	$t_{ m DH}$	10		10		ns	5
Address Hold Time	$t_{ m AH}$	0		0		ns	5
WE Data-Off Time	$t_{ m WEZ}$		40		50	ns	
Write Recovery Time	$t_{ m WR}$	10		10		ns	

WRITE CYCLE TIMING—WRITE-ENABLE CONTROLLED (See Note 5)



WRITE CYCLE TIMING—CE/CE2-CONTROLLED (See Note 5)




POWER-UP/DOWN CHARACTERISTICS—5V

(V_{CC} = 5.0V ±10%, T_A = Over the Operating Range.)

100 old 1 = 1070, 1A o tol allo o polatili g t tall golf							
PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES	
CE or WE at V _{IH} , CE2 at V _{IL} , Before Power-Down	t_{PD}	0			μs		
V_{CC} Fall Time: $V_{PF(MAX)}$ to $V_{PF(MIN)}$	t_{F}	300			μs		
V_{CC} Fall Time: $V_{PF(MIN)}$ to V_{SO}	$t_{ m FB}$	10			μs		
V _{CC} Rise Time: V _{PF(MIN)} to V _{PF(MAX)}	$t_{ m R}$	0			μs		
Power-Up Recover Time	$t_{ m REC}$			35	ms		
Expected Data-Retention Time (Oscillator On)	t_{DR}	10			years	6, 7	

POWER-UP/DOWN TIMING (5V DEVICE)




POWER-UP/DOWN CHARACTERISTICS—3.3V

(V_{CC} = 3.3V ±10%, T_A = Over the Operating Range.)

PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
CE or WE at V _{IH} , Before Power-Down	t_{PD}	0			μs	
V_{CC} Fall Time: $V_{PF(MAX)}$ to $V_{PF(MIN)}$	$t_{ m F}$	300			μs	
V_{CC} Rise Time: $V_{PF(MIN)}$ to $V_{PF(MAX)}$	t_{R}	0			μs	
V _{PF} to \overline{RST} High	$t_{ m REC}$			35	ms	
Expected Data-Retention Time (Oscillator On)	t_{DR}	10			years	6, 7

POWER-UP/DOWN WAVEFORM TIMING (3.3V DEVICE)



CAPACITANCE

 $(T_A = +25^{\circ}C)$

PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Capacitance on All Input Pins	C_{IN}			7	pF	
Capacitance on All Output Pins	Co			10	pF	

AC TEST CONDITIONS

Output Load: 50 pF + 1TTL Gate Input Pulse Levels: 0 to 3.0V

Timing Measurement Reference Levels:

Input: 1.5V Output: 1.5V

Input Pulse Rise and Fall Times: 5ns

NOTES:

- 1) Voltages are referenced to ground.
- 2) Typical values are at +25°C and nominal supplies.
- 3) Outputs are open.
- 4) Battery switchover occurs at the lower of either the battery terminal voltage or V_{PF}.
- 5) The CE2 control signal functions the same as the $\overline{\text{CE}}$ signal except that the logic levels for active and inactive levels are opposite. If CE2 is used to terminate a write, the CE2 data hold time (t_{DH}) applies.
- 6) Data-retention time is at +25°C.
- 7) Each DS1743 has a built-in switch that disconnects the lithium source until V_{CC} is first applied by the user. The expected t_{DR} is defined for DIP modules as a cumulative time in the absence of V_{CC} starting from the time power is first applied by the user.
- 8) RTC Encapsulated DIP Modules (EDIP) can be successfully processed through conventional wave-soldering techniques as long as temperatures as long as temperature exposure to the lithium energy source contained within does not exceed +85°C. Post-solder cleaning with water-washing techniques is acceptable, provided that ultrasonic vibration is not used. See the PowerCap package drawing for details regarding the PowerCap package.

PACKAGE INFORMATION

For the latest package outline information, go to www.maxim-ic.com/DallasPackInfo.

28-pin 740 EDIP Module Document number: <u>56-G0002-001</u>

32-pin PowerCap Module Document number: <u>56-G0003-001</u>



WHAT'S NEW PRODUCTS SOLUTIONS

			SITE SEARCH	PART NO SEARCH		
DESIGN	APPNOTES	SUPPORT	BUY	COMPANY	MEMBERS	

DS1743

Part Number Table

Notes:

- 1. See the DS1743 QuickView Data Sheet for further information on this product family or download the DS1743 full data sheet (PDF, 316kB).
- 2. Other options and links for purchasing parts are listed at: http://www.maxim-ic.com/sales.
- 3. Didn't Find What You Need? Ask our applications engineers. Expert assistance in finding parts, usually within one business day.
- 4. Part number suffixes: T or T&R = tape and reel; + = RoHS/lead-free; # = RoHS/lead-exempt. More: See full data sheet or Part Naming Conventions.
- 5. * Some packages have variations, listed on the drawing. "PkgCode/Variation" tells which variation the product uses.

Part Number	Free Sample	Buy Direct	Package: TYPE PINS SIZE DRAWING CODE/VAR *	Temp	RoHS/Lead-Free? Materials Analysis
DS1743-85+	Sample	Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28+2*	0°C to +70°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743-85IND+		Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28+2*	-40°C to +85°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743-100		Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28-2*	0°C to +70°C	RoHS/Lead-Free: No Materials Analysis
DS1743-100+	Sample	Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28+2*	0°C to +70°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743W-120		Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28-2*	0°C to +70°C	RoHS/Lead-Free: No Materials Analysis
DS1743W-150		Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF)	0°C to +70°C	RoHS/Lead-Free: No Materials Analysis

		Use pkgcode/variation: MDF28-2*		
DS1743W-120+	Sample Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28+2*	0°C to +70°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743W-150+	Sample Buy	MOD;28 pin;600	0°C to +70°C	RoHS/Lead-Free: Yes
	Sample	Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28+2*		Materials Analysis
DS1743W-120IND+	Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF)	0°C to +70°C	RoHS/Lead-Free: Yes
		Use pkgcode/variation: MDF28+2*		Materials Analysis
DS1743W-120 IND	Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28-2*	-40°C to +85°C	RoHS/Lead-Free: No Materials Analysis
DS1743-100 IND	Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28-2*	-40°C to +85°C	RoHS/Lead-Free: No Materials Analysis
DS1743-100IND+	Buy	MOD;28 pin;600 Dwg: 56-G0002-001A (PDF) Use pkgcode/variation: MDF28+2*	-40°C to +85°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743WP-120IND+		, 5	400C to 10E0C	•
D51743WP-120IND+	Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1+2*	-40°C to +85°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743WP-120+	Sample Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF)	0°C to +70°C	RoHS/Lead-Free: Yes
		Use pkgcode/variation: PC1+2*		Materials Analysis
DS1743WP-150	Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1-2*	0°C to +70°C	RoHS/Lead-Free: No Materials Analysis
DS1743WP-120	Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1-2*	0°C to +70°C	RoHS/Lead-Free: No Materials Analysis
DS1743WP-150+	Sample Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF)	0°C to +70°C	RoHS/Lead-Free: Yes
DC1742WD 120TY		Use pkgcode/variation: PC1+2*	40001 .0500	Materials Analysis
DS1743WP-120IND	Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1-2*	-40°C to +85°C	RoHS/Lead-Free: No Materials Analysis

Didn't Find What You Need?





WHAT'S NEW PRODUCTS SOLUTIONS

			SITE SEARCH	SITE SEARCH	
DESIGN	APPNOTES	SUPPORT	BUY	COMPANY	MEMBERS

DS1743P

Part Number Table

Notes:

- 1. See the DS1743P QuickView Data Sheet for further information on this product family or download the DS1743P full data sheet (PDF, 316kB).
- 2. Other options and links for purchasing parts are listed at: http://www.maxim-ic.com/sales.
- 3. Didn't Find What You Need? Ask our applications engineers. Expert assistance in finding parts, usually within one business day.
- 4. Part number suffixes: T or T&R = tape and reel; + = RoHS/lead-free; # = RoHS/lead-exempt. More: See full data sheet or Part Naming Conventions.
- 5. * Some packages have variations, listed on the drawing. "PkgCode/Variation" tells which variation the product uses.

Part Number	Free Sample	Buy Direct	Package: TYPE PINS SIZE DRAWING CODE/VAR *	Temp	RoHS/Lead-Free? Materials Analysis
DS1743P-C01+		Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1+2*	0°C to +70°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743P-85+	Sample	Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1+2*	0°C to +70°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743P-85IND+		Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1+2*	-40°C to +85°C	RoHS/Lead-Free: Yes Materials Analysis
DS1743P-100		Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1-2*	0°C to +70°C	RoHS/Lead-Free: No Materials Analysis
DS1743P-100IND		Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1-2*	0°C to +70°C	RoHS/Lead-Free: No Materials Analysis
DS1743P-100IND+		Buy	PWRCP;34 pin;960 Dwg: 56-G0003-001A1 (PDF)	0°C to +70°C	RoHS/Lead-Free: Yes

DS1743P-100+

Buy Sample

PWRCP;34 pin;960

Dwg: 56-G0003-001A1 (PDF) Use pkgcode/variation: PC1+2*

Use pkgcode/variation: PC1+2*

0°C to +70°C

Materials Analysis RoHS/Lead-Free: Yes

Materials Analysis

Didn't Find What You Need?

✓ CONTACT US: FEEDBACK, QUESTIONS ■★★ RATE THIS PAGE

MAIL THIS PAGE

Copyright © 2007 by Maxim Integrated Products, Dallas Semiconductor • Legal Notices • Privacy Policy