TECHNICAL DATA DATA SHEET 671, REV. B

SCHOTTKY RECTIFIER Very Low Forward Voltage

Applications:

• Switching Power Supply • Converters • Free-Wheeling Diodes • Polarity Protection Diode

Features:

- Soft Reverse Recovery at Low and High Temperature
- Low Forward Voltage Drop
- Low Power Loss, High Efficiency
- High Surge Capacity
- Guard Ring for Enhanced Durability and Long Term Reliability
- Guaranteed Reverse Avalanche Characteristics
- Add Prefix C to SHD For Ceramic Seals (SHDC)
- Add Suffix SS For JANS Screening

Maximum Ratings:

Characteristics	Symbol	Condition	Max.	Units
Peak Inverse Voltage	V_{RWM}	-	45	V
Max. Average Forward Current	I _{F(AV)}	50% duty cycle, rectangular wave form (Single & Doubler)	7.5	Α
Max. Average Forward Current	I _{F(AV)}	50% duty cycle, rectangular wave form (Common Anode & Common Cathode)	15	Α
Max. Peak One Cycle Non- Repetitive Surge Current	I _{FSM}	8.3 ms, half Sine wave (per leg)	75	Α
Max. Thermal Resistance	$R_{\theta JC}$	(per leg)	4.1	°C/W
Max. Junction Temperature	TJ	-	-65 to +150	°C
Max. Storage Temperature	T _{stg}	-	-65 to +150	°C


Electrical Characteristics:


Characteristics	Symbol	Condition	Max.	Units
Max. Forward Voltage Drop	V_{F1}	@ 7.5A, Pulse, T _J = 25 °C	0.65	V
		(per leg)		
	V_{F2}	@ 7.5A, Pulse, T _J = 125 °C	0.60	V
		(per leg)		
Max. Reverse Current	I_{R1}	$@V_R = 45V$, Pulse,	0.75	mA
		T _J = 25 °C (per leg)		
	I_{R2}	$@V_R = 45V$, Pulse,	35	mA
		T _J = 125 °C (per leg)		
Max. Junction Capacitance	C_{T}	$@V_R = 5V, T_C = 25 ^{\circ}C$	400	pF
		$f_{SIG} = 1MHz,$		
		$V_{SIG} = 50 \text{mV (p-p) (per leg)}$		

SENSITRON

TECHNICAL DATA DATA SHEET 671, REV. -

Mechanical Dimensions: In Inches / mm







PINOUT TABLE

TYPE	PIN 1	PIN 2	PIN 3
SINGLE RECTIFIER	CATHODE	ANODE	ANODE
DUAL RECTIFIER, COMMON CATHODE (P)	ANODE 1	COMMON CATHODE	ANODE 2
DUAL RECTIFIER, COMMON ANODE (N)	CATHODE 1	COMMON ANODE	CATHODE 2
DUAL RECTIFIER, DOUBLER (D)	ANODE	ANODE/CATHODE	CATHODE

Note: The V_f curves shown are for the SD090SA45 un-packaged die only.





Reverse Voltage - V_R (V)

0



TECHNICAL DATA

DISCLAIMER:

- 1- The information given herein, including the specifications and dimensions, is subject to change without prior notice to improve product characteristics. Before ordering, purchasers are advised to contact the Sensitron Semiconductor sales department for the latest version of the datasheet(s).
- 2- In cases where extremely high reliability is required (such as use in nuclear power control, aerospace and aviation, traffic equipment, medical equipment, and safety equipment), safety should be ensured by using semiconductor devices that feature assured safety or by means of users' fail-safe precautions or other arrangement.
- 3- In no event shall Sensitron Semiconductor be liable for any damages that may result from an accident or any other cause during operation of the user's units according to the datasheet(s). Sensitron Semiconductor assumes no responsibility for any intellectual property claims or any other problems that may result from applications of information, products or circuits described in the datasheets.
- 4- In no event shall Sensitron Semiconductor be liable for any failure in a semiconductor device or any secondary damage resulting from use at a value exceeding the absolute maximum rating.
- 5- No license is granted by the datasheet(s) under any patents or other rights of any third party or Sensitron Semiconductor.
- 6- The datasheet(s) may not be reproduced or duplicated, in any form, in whole or part, without the expressed written permission of Sensitron Semiconductor.
- 7- The products (technologies) described in the datasheet(s) are not to be provided to any party whose purpose in their application will hinder maintenance of international peace and safety nor are they to be applied to that purpose by their direct purchasers or any third party. When exporting these products (technologies), the necessary procedures are to be taken in accordance with related laws and regulations.