


Product Features

- Doherty amplifier design
- · GaN on SiC HEMT
- · Small and light weight
- 50 Ohm Input/Output impedance matched
- Highly reliable and rugged design
- · High efficiency
- 10W, 12W typical PAVG

Application

- WCDMA, LTE DPD amplifier
- General purpose RF amplifier



Description

The RTP26010-N1 is designed for RF system application frequencies from 2570MHz to 2690MHz, with high gain. This Pallet Amplifier uses GaN on SiC HEMT technology which performs high breakdown voltage, high linearity, high efficiency. The RTP26010-N1 is DPD application amplifier.

Electrical Specifications @ VDD=+28VDC, T=25°C, 50Ω

PARAMETER	Symbol	Min	Тур	Max	Unit
Frequency Range	BW	2570	-	2690	MHz
Output Power	P_{AVG}	-	10	12	Watt
Output Power @ Psat G.C.P	P _{sat}	-	47.5	-	Watt
Small Signal Gain	SSG	-	40	-	dB
Small Signal Gain Flatness	ΔG	-	± 1.0	± 2	dB
Gain Variation	ΔGt		± 3.0	-	dB
ACLR @ WCDMA 20MHz 4FA	ACLR	-25	-30	-	dBr
ACLR with DPD	ACLR	-	-50	-	dBr
Forward Coupling	FC	-	-30	-	dB
Operating Voltage	VDC	-	28	-	Volt
Efficiency @ Pout 10Watt WCDMA	Е	-	38	-	%
Efficiency @ Pout 12Watt LTE	Е	-	40	-	%

^{*} Test Signal Condition: WCDMA 20MHz 4FA (PAR 7.5dB), LTE 10MHz 1FA (PAR 6.5dB), Test DPD solution: Opticron DPD

Environmental Characteristics

PARAMETER	Symbol	Min	Тур	Max	Unit
Operating Temperature	Te	-30	-	+60	°C
Storage Temperature	Ts	-40	-	+90	°C

Mechanical Specifications

PARAMETER	Value	Units	Limits
Dimensions (L x W x H)	100 x 50 x 20	mm	Max
Weight	170	g	Typical
RF Connectors In/Out/Coupling	MCX / SMA / MCX Female		
DC Connectors / Controls	5267-04		
Cooling	External Heat sink + airflow		

Tel: 82-31-250-5078rfsales@rfhic.com

[•] All specifications may change without notice.

[•] Version 0.1



RF Interface Connectors


Pin #	DESCRIPTION	Specifications	
1	RF IN	RF Input signal from TRx B'd	
2	RF OUT	RF Output signal	
3	RF FWD Port	RF Forward Detection signal For Feed-back	


DC Connector


Pin #	DESCRIPTION	Specifications
1	Gain Block Amp +Vgg	+5.6Vdc
2	Vdd	+28Vdc
3	Vdd	+28Vdc
4	GND	Ground


^{*} RF connector and DC connector custom design available.


Outline Drawing















Typical Output Spectrum @ WCDMA 20MHz 4FA (PAR 7.5dB): Pout =10W(40dBm)


Frequency 2.58GHz



Frequency 2.68GHz




Frequency 2.63GHz






Typical Output Spectrum @ LTE 10MHz 1FA (PAR 6.5dB): Pout =12W(41dBm)


Frequency 2.58GHz



Frequency 2.63GHz



Frequency 2.68GHz



RFHIC Corporation (RFHIC) reserves the right to make changes to any products herein or to discontinue any product at any time without notice. RFHIC do not RFHIC Corporation (RFHIC) reserves the right to make changes to any products herein or to discontinue any product at any time without notice. RFHIC do not assume any liability for the suitability of its products for any particular purpose, and disclaims any and all liability, including without limitation consequential or incidental damages. The product specifications herein expressed have been carefully checked and are assumed to be reliable. However, RFHIC disclaims liability for inaccuracies and strongly recommends buyers to verify that the information they are using is current before placing purchase orders. RFHIC products are not intended for use in life support equipment or application where malfunction of the product can be expected to result in personal injury or death. Buyer uses or sells such products for any such unintended or unauthorized application, buyer shall indemnify, protect and hold RFHIC and its directors, officers, stockholders, employees, representatives and distributors harmless against any and all claims arising out of such use. RFHIC's liability under or arising out of damages, claims of whatsoever kind and nature which RFHIC products could cause shall be limited in amount to the net purchase price of the products sold to buyer by RFHIC.

■ Tel: 82-31-250-5078

All specifications may change without notice.