

# **ELECTRO-PNEUMATIC CONVERTER**

DATA SHEET

ZLC

The electro-pneumatic converter installed in site converts a 4 to 20mA DC operation signals from an electronic controller into proportional 19.6 to 98.1 kPa {0.2 to 1.0kgf/cm²} pneumatic signals for transmitting to pneumatic positioner, or operating pneumatic final control elements such as diaphragm valves, etc.

### **FEATURES**

1. High conversion accuracy

The guaranteed conversion accuracy is within 0.75%.

2. Various types

Flame-proof type, intrinsically safe explosion-proof type, split range type, etc. are available.

3. A low input resistance of  $200\Omega$  permits two converters to simultaneously operate.



## **SPECIFICATIONS**

Input signal: 4 to 20mA DC, 4 to 12mA DC or 12 to

20mA DC

Input resistance : Approx.  $200\Omega$  (at  $20^{\circ}$ C) Accuracy rating :  $\pm 0.75\%$  of full range Hysteresis : 0.5% of full range Response time : Approx. 0.7 sec

(90% time of full range when the load ca-

pacity ia 0.5  $\ell$  )

Air supply pressure and output signal:

Air supply pressure [kPa] {kgf/cm²}	Output signal
[kPa] {kgf/cm²}	[kPa] {kgf/cm²}
140 {1.43}	19.6 to 98.1 {0.2 to 1.0} 39.2 to 196.1 {0.4 to 2.0}
240 {2.45}	39.2 to 196.1 {0.4 to 2.0}

Output signal pressure gauge:

As specified by the customer JIS class 3 with the graduation angle of 270°

Input/output operations:

As specified by the customer

Normal action;

The output signal level increases as the input signal level increases.

Reverse action;

The output signal level decreases as the input signal level increases.

Nominal air consumption:

12N ℓ /min (at the supply air pressure of

140kPa{1.43kgf/cm<sup>2</sup>})

20N ℓ /min (at the supply air pressure of

240kPa{2.45kgf/cm<sup>2</sup>})

Maximum air consumption :

60N  $\ell$  /min (at the supply air pressure of

140kPa{1.43kgf/cm²})

80N  $\boldsymbol\ell$  /min (at the supply air pressure of

240kPa{2.45kgf/cm<sup>2</sup>})

Ambient temperature:

-20 to +80°C

Intrinsically safe explosion-proof type;

–20 to +60°C

Flame-proof type;  $-20 \text{ to } +70^{\circ}\text{C}$ 

Ambient humidity:

Less than 95% RH

External dimensions  $(H \times W \times D)$ :

176 × 176 × 124mm

Mas{weight}: Approx. 3kg

Air pipe connection:

Rc1/4 or NPT1/4 adapter

Conduit connection:

 $G^{1/2}$ 

Waterproof structure:

Splash proofing (JIS C 0920)

Explosion-proof structure:

Intrinsically safe explosion-proofing (JIS i3nG5)

Flame-proofing (JIS d2G4) Finish color: Silver (epoxy resin coating) Acid and alkali-proofing treatment:


> Mounting U-bolts, nuts and washers made of stainless steel are used upon request

Mounting method:


Connected to pipe 50A (2B) or mounted on

the wall.


## **FUNDAMENTAL BLOCK DIAGRAM**




## **CODE SYMBOLS**



# **OUTLINE DIAGRAM (Unit: mm)**





<GENERAL USE and INTRINSICALLY SAFE EXPLOSION-PROOF TYPES>



Note: \*shows the part used for the flame-proof packing type which used for 11mm diameter cable.


#### <FLAME-PROOF TYPE>







Note: \*shows the part used for the flame-proof packing type which used for 11mm diameter cable.

<FLAME-PROOF TYPE>







Commection diagram

## **RELATED DEVICES**

Electro-pneumatic positioner Diaphragm type control valve Opener (FXZ2 type)

## **ORDERING INFOMATION**

- 1. Product name
- 2. Code symbol
- 3. Other requirements

#### 

\*Before using this product, be sure to read its instruction manual in advance.

# Fuji Electric Systems Co., Ltd.

### **Head Office**

6-17, Sanbancho, Chiyoda-ku, Tokyo 102-0075, Japan http://www.fesys.co.jp/eng

#### Sales Div.

#### International Sales Dept.

No.1, Fuji-machi, Hino-city, Tokyo, 191-8502 Japan Phone: 81-42-585-6201, 6202 Fax: 81-42-585-6187

http://www.fic-net.jp/eng