



Ordering Code	Inductance L (μH)	fL (MHz)	Tol. %	Q min.	Testing Freq. (MHz)	SRF (MHz) min.	Dc-Res (Ω) max.	Rated DC Current (mA)
HACC-1R0K - **	1.0	1.0	±10	50	7.96	195	0.08	2.00
HACC-1R2K - **	1.2					180	0.09	1.80
HACC-1R5K - **	1.5					165	0.10	1.70
HACC-1R8K - **	1.8					155	0.11	1.65
HACC-2R2K - **	2.2					140	0.12	1.60
HACC-2R7K - **	2.7			125	0.13	1.50		
HACC-3R3K - **	3.3			115	0.14	1.45		
HACC-3R9K - **	3.9			105	0.15	1.40		
HACC-4R7K - **	4.7			60	0.17	1.30		
HACC-5R6K - **	5.6			45	0.19	1.25		
HACC-6R8K - **	6.8	35	0.22	1.20				
HACC-8R2K - **	8.2	25	0.24	1.15				
HACC-100K - **	10.0	21	0.25	1.10				
HACC-120K - **	12.0	17	0.27	1.05				
HACC-150K - **	15.0	16	0.30	1.00				
HACC-180K - **	18.0	15	0.33	0.95				
HACC-220K - **	22.0	13	0.37	0.90				
HACC-270K - **	27.0	11	0.42	0.85				

↑ FERRITE ↓