



BZT52C43 - BZT52C51

SURFACE MOUNT ZENER DIODE

Features

- Planar Die Construction
- General Purpose, Medium Current
- Ideally Suited for Automated Assembly Processes
- Lead, Halogen and Antimony Free, RoHS Compliant "Green" Device (Notes 5 and 6)

Mechanical Data

- Case: SOD-123
- Case Material: Molded Plastic. UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020D
- Terminals: Solderable per MIL-STD-202, Method 208
- Lead Free Plating (Matte Tin Finish annealed over Alloy 42 leadframe)
- Polarity: Cathode Band
- Marking Information: See Page 2
- Ordering Information: See Page 2
- Weight: 0.01 grams (approximate)



Top View

Thermal Characteristics

Characteristic	Symbol	Value	Unit		
Power Dissipation (Note 1)	PD	410	mW		
Thermal Resistance, Junction to Ambient Air (Note 1)	$R_{ extsf{ heta}JA}$	305	°C/W		
Operating and Storage Temperature Range	T _J , T _{STG}	-65 to +150	°C		

Electrical Characteristics @T_A = 25°C unless otherwise specified

Туре	Marking Code	Zener Voltage Rang (Note 2)			ge	Maximum Ze	Maximum Reverse Current (Note 2)			
Number	(Note 3)	Vz @ Izt		I _{ZT}	Z _{ZT} @ I _{ZT} Z _{ZK} @ I _{ZK}		I _{ZK}	I _R	@ V _R	
		Nom (V)	Min (V)	Max (V)	mA	Ω	Ω		uA	v
BZT52C43	WU/WU	43	40.0	46.0	5	100	700	1.0	0.1	32
BZT52C47	WV/WZ	47	44.0	50.0	5	100	750	1.0	0.1	35
BZT52C51	WW/X1	51	48.0	54.0	5	100	750	1.0	0.1	38

1. Device mounted on ceramic PCB; 7.6mm x 9.4mm x 0.87mm with pad areas 25mm².

Short duration pulse test used to minimize self-heating effect. 2.

When provided, otherwise, parts are provided with date code only, and type number identification appears on reel only. 3.


f = 1kHz4.

Notes:

5.

No purposefully added lead. Halogen and Antimony Free. Product manufactured with Data Code V9 (week 33, 2008) and newer are built with Green Molding Compound. Product manufactured prior to Date Code V9 are built with Non-Green Molding Compound and may contain Halogens or Sb₂O₃ Fire Retardants. 6.








Ordering Information (Note 7)

*Replace "XX" with the nominal Zener breakdown voltage; i.e. Part number for 43V device would be BZT52C43-7-F.

Notes: 7. For packaging details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf.

Marking Information




xx = Product Type Marking Code (See Electrical Characteristics Table) YM = Date Code Marking Y = Year (ex: N = 2002)

M = Month (ex: 9 = September)

Date Code Ke	ey							_							
Year	1998	1999	2000	2001	2002	2003	2004	200	5 2006	2007	2008	2009	2010	2111	2012
Code	J	К	L	М	Ν	Р	R	S	Т	U	V	W	Х	Y	Z
Month	Jan	Fe	b	Mar	Apr	May	Ju	n	Jul	Aug	Sep	Oc	t I	Nov	Dec
Code	1	2		3	4	5	6		7	8	9	0		Ν	D

Case

SOD-123




C47

10

T_J = 25°C

BZT52C43 - BZT52C51




Packaging


3000/Tape & Reel



Package Outline Dimensions



Suggested Pad Layout



Dimensions	Value (in mm)
Z	4.9
G	2.5
Х	0.7
Y	1.2
C	3.7

IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.