

# Omni Antennas

Based on patented technology, Andrew Omni Antennas have superior performance, outstanding reliability and excellent durability.

Omni Antennas are designed for an aesthetically pleasing appearance and low wind loading.

Andrew Base Station Antennas are also available for other frequency bands and beamwidths. Please contact your Andrew Representative for additional information.

# **Key Performance Advantages:**

## Superior Wideband Performance:

- Omnidirectional, bidirectional and sector configurations
- Variety of patterns and gains
- Low VSWR across frequency band
- Electrical downtilt and null-fill options for excellent near-in coverage

# Outstanding Reliability:

- · Patented design requires fewer internal components
- Reduced intermodulation (IM) generation and internal connection/element failure from wind and vibration

#### Excellent Durability:

 High Strength Radome minimizes beam deflection, maintains beam integrity, ensures long service life in extreme climates

#### Flexible Electrical Design:

- Gain, downtilt, bandwidth, and patterns to meet your needs
- · Customized solutions available

Regio Amemies

Pot Sill Antennas



## PG900 Product Range

Model Number	Туре	Frequency MHz	Gain dBd (dBi)	Downtilt Degree
PG1N0F-0091-006	Omni (Rx)	901–902	4 (6)	0
PG1N0F-0091-009	Omni (Rx)	901-902	7 (9)	0
PG1N0F-0091-011	Omni (Rx)	901–902	9 (11)	0
PG1N0F-0091-111	Omni (Rx)	901–902	9 (11)	1
PG1N0F-0091-311	Omni (Rx)	901–902	9 (11)	3
PG1N0F-0091-608	Omni (Rx)	901-902	6 (8)	6
PG1N0F-0091-610	Omni (Rx)	901–902	8 (10)	6
PG1*0F-0093-006	Omni (Tx)	928-944	4 (6)	0
PG1*0F-0093-009	Omni (Tx)	928-944	7 (9)	0
PG1*0F-0093-011	Omni (Tx)	928-944	9 (11)	0
PG1*0F-0093-209	Omni (Tx)	928-944	7 (9)	2
PG1*0F-0093-311	Omni (Tx)	928-944	9 (11)	3
PG1*0F-0093-606	Omni (Tx)	928-944	4 (6)	6
PG1*0F-0093-608	Omni (Tx)	928-944	6 (8)	6
PG1*0F-0093-610	Omni (Tx)	928-944	8 (10)	6
PG1*0F-0093-810	Omni (Tx)	928-944	8 (10)	8
PG1*0F-0090-011	Omni	901-944	9 (11)	0
PG7*0F-0090-013	Cardioid	901-944	11 (13)	0
PG7*0F-0090-014	Cardioid	901-944	12 (14)	0
PG1*0F-0090-310	Omni	901-944	8 (10)	3
PG7*0F-0090-313	Cardioid	901-944	11 (13)	3
PG7*0F-0090-314	Cardioid	901-944	12 (14)	3
* N. Type "N" Connector	D 716 DU	N Connector		

\* N= Type "N" Connector D= 7-16 DIN Connector

#### **Model Numbering System**

Six fields fully define each model and available options. For example:

PG 1 N0F - 0091 - 0 09 ① ② ③ ④ ⑤ ⑥ (PG1N0F-0091-009)

① Application: PG = Paging

② Pattern: 1 = Omni Directional 7 = 180° Sector

 $\ensuremath{ \ \ \, }$  Connector: N = Type N connector, female

D = 7-16 DIN connector, female

④ Frequency:

0090 = 901 - 944 MHz 0091 = 901 - 902 MHz 0093 = 928 - 944 MHz

⑤ Degree of Downtilt

Nominal gain (dBi)

#### **Electrical Characteristics**

 Impedance:
 50 ohms

 Return Loss (VSWR):
 >14.0 dB (<1.5:1)</td>

Polarization: Vertical

**Power:** Continuous >500 W (-0090, -0093)

>100 W (-0091)

Peak >4 kW

# Omni Antennas Characteristics

# PC1900 Product Range

Model Number	Туре	Frequency MHz	Gain dBd (dBi)	Downtilt Degree		
PC1N0F-0190A-002	Omni	1850-1990	0 (2)	0		
PC1*0F-0190A-006	Omni	1850-1990	4 (6)	0		
PC1*0F-0190-008	Omni	1850-1990	6 (8)	0		
PC1*0F-0190-010	Omni	1850-1990	8 (10)	0		
225077**	Magnet	1850-1990	0 (2)	0		
Mount Omni						

<sup>\*</sup> N= Type "N" Connector D= 7-16 DIN Connector

#### **Model Numbering System**

Three fields fully define each model and available options. For example:

PC 1 NOF - 0190A - 0 06 ① ② ③ ④ ⑤ ⑥ (PC1N0F-0190A-006)

① Application: PC = Personal Communications

2 Pattern: 1 = Omni Directional

③ Connector: N0F = Type N connector, female D0F = 7-16 DIN connector, female

Frequency and product revision:0190A = 1850-1990 MHz, revision A

⑤ Degree of Downtilt

Nominal gain (dBi)

#### **Enviromental Characteristics**

Survival Wind Speed: 56 m/s (200 km/h) 125 mph

Temperature: -40°C to 55°C
Humidity: Up to 100%
Lightning Protection: DC ground

# **Mechanical Characteristics**

Support Pipe Material: Aluminum

Radome Material: UV Protected Fiberglass

Radome Color: Gray

Mounting Hardware: Ordered Separately

#### **Electrical Characteristics**

Frequency Range: 1850 - 1990 MHz Impedance: 50 ohms

**Return Loss (VSWR):** >14.0 dB (<1.5:1) **Polarization:** Vertical

Power: Continuous >200 W
Peak >4 kW



<sup>\*\*</sup> Mechanical specs do not apply to magnet mount version