

## **Platinum Resistance Temperature Detector**

C 220

The C series thin-film PRTDs combine the ideal curve characteristics of ceramic wire-wound RTDs with the vibration resistance of glass wire-wound RTDs and represent an excellent alternative to wire-wound RTDs. They are characterized by high long-term stability, excellent temperature shock resistance and a wide temperature range of -196°C to +150°C. The deviation from the DIN EN 60751 (according to IEC 751) characteristic curve is minimal over the entire temperature range, they show no hysteresis. These features make them best suited for applications in aerospace, chemical and power generation plants and analytical equipment.

Nominal Resistance R0	<b>Tolerance</b> DIN EN 60751 1996-07	<b>Tolerance</b> DIN EN 60751 2009-05	Order Number Plastic Box
100 Ohm at 0°C	Class B	F 0.3	32 207 399

The measuring point for the nominal resistance is defined at 8mm from the end of the sonsor body.

**DIN EN 60751** Specification

Nominal resistance  $100\Omega$  at 0°C

-196°C to +150°C Temperature range

Tolerance Class B: -196°C to +150°C

Temperature coefficient TC= 3850 ppm/K

AgPd-wire Leads

Lead lengths (L) 10mm ±1mm

Long-term stability max. R0-Drift 0.03% after 1000 h at 150°C

**Environmental conditions** unhoused for dry environments only

at least 40g acceleration at 10 to 2000 Hz, Vibration resistance

depends on installation

Shock resistance at least 100g acceleration with 8ms

half sine wave, depends on installation

Insulation resistance > 100 MΩ at 150°C

0.4 K/mW at 0°C Self heating

Response time water current (v= 0.4m/s):  $t_{0.5} = 0.06s$ 

 $t_{0.9} = 0.20s$ 

air stream (v= 2m/s):  $t_{0.5} = 3.5s$ 


 $t_{0.9} = 13.0s$ 

Measuring current 100Ω: 0.3 to 1.0mA

(self heating has to be considered)

Other tolerances, values of resistance and wire lengths are Note

available on request.



**Heraeus Sensor Technology USA** 1901 Route 130

North Brunswick, NJ 08902

Phone 732-940-4400 Fax 732-940-4445

Email info.hst-us@heraeus.com

http://heraeus-sensor-technology-us.com

