



## Shorting Dust Cap for BNC Female With 4 Inch Chain

## **TECHNICAL DATA SHEET**

PE6128

## Shorting Dust Cap for BNC Female With 4 Inch Chain

Configuration

Connector **BNC Female Shorting** 

Chain Option 4 In. Chain

**Mechanical Specifications** 

Size

Length, in [mm] 0.66 [16.76] Width, in [mm] 0.5 [13]

Connector

Type **BNC Female Shorting** 

Contact Material and Plating Silver **Body Material and Plating** Brass, Nickel

Compliance Certifications (visit www.Pasternack.com for current document)

**RoHS Compliant** 

**Plotted and Other Data** 

Notes: Values at 25 °C, sea level

Shorting Dust Cap for BNC Female With 4 Inch Chain from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Shorting Dust Cap for BNC Female With 4 Inch Chain PE6128

URL: http://www.pasternack.com/50-ohm-bnc-female-short-cap-with-4-inch-chain-pe6128-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

PF6128 RFV



PE6128 CAD Drawing
Shorting Dust Cap for BNC Female With 4 Inch Chain

