

## 1:1 Broadband CATV, Flux Coupled Transformer 5-120MHz

MABACT0047

#### **Features**

- Surface Mount
- 1:1 Flux Coupled
- 260°C Reflow Compatible
- Excellent temperature stability
- Available on Tape and Reel. Reel quantity 2000

### **Description**

M/A-COM's MABACT0047 is a low cost 1:1 Flux Coupled Transformer designed for high volume CATV Broadband applications. Suitable for use in 50 Ohm and 75 Ohm systems



### **Pin Configuration**


Pin No.	Function		
1	Secondary Dot (output 1)		
2	Centre Tap		
3	Secondary (output 2)		
4	Primary (ground)		
5	Primary Dot (input)		

## **Ordering Information**


Part Number	Package		
MABACT0047	Reel Quantity 2000		


Note: Reference Application Note M513 for reel size information.

### **Schematic**



## Case Style: SM-22A





Dimensions in inches [mm] Tolerance: .xx ± .02, .xxx ± .010

ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed.

PRELIMINARY: Data Sheets contain information regarding a product M/A-COM Technology

Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.

<sup>•</sup> North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400

<sup>•</sup> India Tel: +91.80.4155721 Visit www.macomtech.com for additional data sheets and product information.

<sup>•</sup> China Tel: +86.21.2407.1588



## 1:1 Broadband CATV, Flux Coupled Transformer 5-120MHz

MABACT0047

# Electrical Specifications: $T_A = 25^{\circ}C$ , $Z_0 = 75\Omega^{1}$


Parameter	Frequency	Units	Min	Тур	Max
Frequency Range:	5 - 120 MHz				
Insertion Loss	5 - 120 MHz	dB	-	0.4	0.6
Amplitude Balance	5 - 120 MHz	dB	-	± 0.1	± 0.3
Phase Balance	5 - 120 MHz	0	-	± 0.5	± 2.0
Input Return Loss	5 - 65 MHz 65 - 120 MHz	dB dB	22 17	28 23	

# **Absolute Maximum Ratings <sup>1,2</sup>**

Parameter	Absolute Maximum		
RF Power	250 mW		
DC current	30mA		
Operating Temperature	-40°C to +85°C		
Storage Temperature	-40°C to +85°C		

- 1. Exceeding any one or combination of these limits may cause permanent damage to this device.
- 2. M/A-COM does not recommend sustained operation near these survivability limits.

## **Recommended PCB Configuration**



<sup>•</sup> North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400

<sup>•</sup> India Tel: +91.80.4155721

<sup>•</sup> China Tel: +86.21.2407.1588 Visit www.macomtech.com for additional data sheets and product information.




# 1:1 Broadband CATV, Flux Coupled Transformer 5-120MHz


MABACT0047

Typical Performance Curves:  $T_A = 25^{\circ}C$ ,  $Z_0 = 75\Omega^{1}$ 


#### **Insertion Loss**




### **Return Loss: Input**



### **Amplitude Balance**



#### **Phase Balance**



<sup>•</sup> India Tel: +91.80.4155721

<sup>•</sup> China Tel: +86.21.2407.1588 Visit www.macomtech.com for additional data sheets and product information.