

# TAI-SAW TECHNOLOGY CO., LTD. No. 3, Industrial 2nd Rd., Ping-Chen Industrial District,

No. 3, Industrial 2nd Rd., Ping-Chen Industrial District,
Taoyuan, 324, Taiwan, R.O.C.

TEL: 886-3-4690038 FAX: 886-3-4697532 E-mail: <a href="mailto:tstsales@mail.taisaw.com">tstsales@mail.taisaw.com</a> Web: <a href="mailto:www.taisaw.com">www.taisaw.com</a>

# **Product Specifications Approval Sheet**

Product Name: Duplexer 173	32.5/2132.5MH	z 45MHz BW SMI	2.0×1.6 mm
TST Parts No.: TF0087A			
Customer Part No.:			_
Customer signature required			
Company:			
Division:			
Approved by :			
Date:			
Checked by:	Andy Yu	Andy In	_
Checked by:	Bob Chau	plelm	_
Date:	2013, 11,13		

- 1. Customer signed back is required before TST can proceed with sample build and receive orders.
- 2. Orders received without customer signed back will be regarded as agreement on the specifications.
- 3. Any specifications changes must be approved upon by both parties and a new revision of specifications shall be released to reflect the changes



# TAI-SAW TECHNOLOGY CO., LTD.

No. 3, Industrial 2nd Rd., Ping-Chen Industrial District, Taoyuan, 324, Taiwan, R.O.C.

TEL: 886-3-4690038 FAX: 886-3-4697532 E-mail: <a href="mailto:tstsales@mail.taisaw.com">tstsales@mail.taisaw.com</a> Web: <a href="mailto:www.taisaw.com">www.taisaw.com</a>

# SAW Duplexer 1732.5/2132.5MHz 45MHz BW SMD 2.0×1.6 mm

MODEL NO.: TF0087A REV. No.: 1.0

#### A. MAXIMUM RATING:

1. Maximum Input Power: 29 dBm

2.DC voltage: 0 V

3.Operating Temperature: -20°C to +85°C 4.Storage Temperature: -40°C to +85°C

**RoHS Compliant** 

Lead-free soldering

#### **B. ELECTRICAL CHARACTERISTICS:**

Tx to Ant			Specif	ications	
Parameters Description	Condition [MHz]	Unit	Minimum	Typical	Maximum
Insertion Loss	1710.0 ~ 1755.0	dB	-	1.8	2.0
Ripple	1710.0 ~ 1755.0	dB	-	0.6	1.0
VSWR of Ant Port	1710.0 ~ 1755.0	-	-	1.6	2.0
VSWR of Tx Port	1710.0 ~ 1755.0	-	-	1.8	2.1
Attenuation	300.0 ~ 1574.0	dB	30	40	-
	1574.0 ~ 1577.0	dB	45	49	-
	1574.0 ~ 1605.0	dB	38	45	-
	1805.0 ~ 1880.0	dB	41	49	-
	1930.0 ~ 1990.0	dB	42	46	-
	2110.0 ~ 2155.0	dB	50	54	-
	2400.0 ~ 2500.0	dB	35	41	-
	3420.0 ~ 3540.0	dB	21	30	-
	5130.0 ~ 5265.0	dB	12	24	-


**Notes**: (1) With Matching Network.

Ant to Rx			Specif	ications	
Parameters Description	Condition [MHz]	Unit	Minimum	Typical	Maximum
Insertion Loss	2110.0 ~ 2155.0	dB	-	1.8	2.0
Ripple	2110.0 ~ 2155.0	dB	-	0.4	0.8
VSWR of Ant Port	2110.0 ~ 2155.0	-	-	1.4	2.0
VSWR of Rx Port	2110.0 ~ 2155.0	-	-	1.6	2.0
Attenuation	300.0 ~ 1710.0	dB	40	47	-
	1710.0 ~ 1755.0	dB	48	51	-
	1755.0 ~ 2025.0	dB	30	41	-
	2240.0 ~ 2400.0	dB	25	30	-
	2400.0 ~ 2484.0	dB	35	41	-
	2484.0 ~ 6000.0	dB	35	43	-
Amplitude balance( S <sub>31</sub> /S <sub>41</sub>  )	2110.0 ~ 2155.0	dB	-1.0	-0.1/+0.7	+1.0
Phase balance Φ(S <sub>31</sub> )-Φ(S <sub>41</sub> )+180*	2110.0 ~ 2155.0	deg	-12	-1/+8	+12


Tx to Rx			Specif	ications	
Parameters Description	Condition [MHz]	Unit	Minimum	Typical	Maximum
Isolation in Tx Band	1710.0 ~ 1755.0	dB	52	55	-
Isolation in Rx Band	2110.0 ~ 2155.0	dB	47	50	-

# C. Frequency Characteristics:


Tx to Ant




#### Ant to Rx




#### **Isolation**




#### **Ripple**




# VSWR (Tx Port)




# **Smith Chart (Tx Port)**




# VSWR (Rx Port)




# **Smith Chart (Rx Port)**



# VSWR (ANT Port)




# **Smith Chart (ANT Port)**




#### Wide Span


Tx




Rx




# Amplitude balance of Ant to Rx+/Rx-




# Phase balance of Ant to Rx+/Rx-




# D. MEASUREMENT CIRCUIT:



# **E.OUTLINE DRAWING:**






Marking Descriptions		
D	Duplexer Application	
4	Band Class	
1	Series Number	
Х	Date Code(Year+Month)	

Pin Description			
B,D,E,G,J	Ground		
F	Ant		
С	Tx (1732.5MHz)		
A,H	Rx (2132.5MHz)		


# **E. PACKING:**

# 1. REEL DIMENSION

(Please refer to FR-75D10 for packing quantity)



# 2.TAPE DIMENSION



# F. RECOMMENDED REFLOW PROFILE:

