


PI74ALVCH16500

18-Bit Universal Bus Transceiver With 3-State Outputs

Product Features

- PI74ALVCH16500 is designed for low voltage operation
- $V_{CC} = 2.3V \text{ to } 3.6V$
- Hysteresis on all inputs
- Typical V_{OLP} (Output Ground Bounce) < 0.8V at $V_{CC} = 3.3V$, $T_A = 25$ °C
- Typical V_{OHV} (Output V_{OH} Undershoot) < 2.0 V at $V_{CC} = 3.3 \text{V}$, $T_A = 25 ^{\circ}\text{C}$
- Bus Hold retains last active bus state during 3-State eliminating the need for external pullup resistors
- Industrial operation at -40°C to +85°C
- Packages available:
 - -56-pin 240 mil wide plastic TSSOP (A)
 - -56-pin 300 mil wide plastic SSOP (V)

Logic Block Diagram



Product Description

Pericom Semiconductor's PI74ALVCH series of logic circuits are produced using the Company's advanced 0.5 micron CMOS technology, achieving industry leading speed.

The 18-bit PI74ALVCH16500 univeral bus transceiver is designed for 2.3V to 3.6V Vcc operation.

Data flow in each direction is controlled by Output Enable (OEAB and OEBA), Latch-Enable (LEAB and LEBA), and clock (CLKAB and CLKBA) inputs. For A- to-B data flow, the device operates in the transparent mode when LEAB is high. When LEAB is low, the A data is latched if CLKAB is held at a high or low logic level. If LEAB is low, the A data is stored in the latch/flip-flop on the highto-low transition of CLKAB. Output-enable OEAB is active high. When OEAB is high, the B-port outputs are active. When OEAB is low, the B-port outputs are in the high-impedence state.

Data flow for B to A is similar to that of A to B but uses OEBA, LEBA, and CLKBA. The Output Enables are complementary (OEAB is active HIGH and \overline{OEBA} is active LOW).

To ensure the high-impedance state during power up or power down, OEBA should be tied to Vcc through a pull-up resistor and OEAB should be tied to GND through a pulldown resistor; the minimum value of the resistor is determined by the current-sinking/ current-sourcing capability of the driver.

Active bus-hold circuitry is provided to hold unused or floating data inputs at a valid logic level.

PS8155A 11/06/00


1



Product Pin Description

Pin Name	Description
ŌĒ	Output Enable Input (Active HIGH)
LE	Latch Enable (Active HIGH)
CLK	Clock Input (Active LOW)
Ax	Data I/O
Bx	Data I/O
GND	Ground
Vcc	Power

Product Pin Configuration



Truth Table(1)†

	Inputs							
OEAB	LEAB	CLKAB	A	Output B				
L	X	X	X	Z				
Н	Н	X	L	L				
Н	Н	X	Н	Н				
Н	L	\	L	L				
Н	L	\	Н	Н				
Н	L	L or H	X	B0‡				

Note:

- 1. H = High Signal Level
 - L = Low Signal Level
 - Z = High Impedance
 - \downarrow = HIGH-to-LOW Transition
- † A-to-B data flow is shown: B-to-A flow is similar but uses OEBA, LEBA, CLKBA.
- ‡ Output level before the indicated steady-state input conditions were established.



Maximum Ratings

(Above which the useful life may be impaired. For user guidelines, not tested.)

Storage Temperature65°C to	+150°C
Ambient Temperature with Power Applied—40°C to	+85°C
Input Voltage Range, V _{IN} –0.5V to V _{CC}	+0.5V
Output Voltage Range, VOUT0.5V to VCC	+0.5V
DC Input Voltage0.5V to	+5.0V
DC Output Current	00 mA
Power Dissipation	1.0W

Note:

Stresses greater than those listed under MAXI-MUM RATINGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

$\textbf{Recommended Operating Conditions} ^{(1)}$

Parameters	Description	Test Conditions	Min.	Тур.	Max.	Units	
V _{CC}	Supply Voltage		2.3		3.6		
* 7	Innut IIICII Voltaga	$V_{CC} = 2.3V \text{ to } 2.7V$	1.7				
$V_{ m IH}$	Input HIGH Voltage	$V_{CC} = 2.7V \text{ to } 3.6V$	2.0				
17-	Innut I OW Vallage	$V_{CC} = 2.3 V \text{ to } 2.7 V$			0.7	V	
$ m V_{IL}$	Input LOW Voltage	$V_{CC} = 2.7V \text{ to } 3.6V$			0.8		
V _{IN}	Input Voltage		0		V _{CC}		
V _{OUT}	Output Voltage		0		V _{CC}		
		$V_{CC} = 2.3V$			-12		
I_{OH}	High-level Output Current	$V_{\rm CC} = 2.7 V$			-12		
		$V_{CC} = 3.0V$			-24		
Iol		$V_{CC} = 2.3V$			12	mA	
	Low-level Output Current	$V_{\rm CC} = 2.7 V$			12		
		$V_{CC} = 3.0V$			24		
TA	Operating Free-Air Temperature		-40		85	°C	

Note:

1. Unused control inputs must be held HIGH or LOW to prevent them from floating.



DC Electrical Characteristics (Over the Operating Range, $TA = -40^{\circ}\text{C}$ to $+85^{\circ}\text{C}$, $VCC = 3.3\text{V} \pm 10\%$)

Parameters	Test Conditions		Vcc ⁽¹⁾	Min.	Typ.(2)	Max.	Units
	$I_{OH} = -100 \mu A$	Min. to Max.	V _{CC} -0.2				
	$I_{OH} = -6mA$	$V_{IH} = 1.7V$	2.3V	2.0			
T 7		$V_{IH} = 1.7V$	2.3V	1.7			
$V_{ m OH}$	$I_{OH} = -12 \text{mA}$	$V_{IH} = 2.0V$	2.7V	2.2			
		$V_{IH} = 2.0V$	3.0V	2.4			
	$I_{OH} = -24$ mA	$V_{IH} = 2.0V$	3.0V	2.0			V
	$I_{OL} = 100 \mu A$		Min. to Max.			0.2	
	$I_{OL} = 6mA$	$V_{IL} = 0.7V$	2.3V			0.4	
V_{OL}	I 12mA	$V_{IL} = 0.7V$	2.3V			0.7	
	$I_{OL} = 12 \text{mA}$	$V_{IL} = 0.8V$	2.7V			0.4	
	$I_{OL} = 24 \text{mA}$	$V_{IL} = 0.8V$	3.0V			0.55	
II	$V_{\rm I} = V_{\rm CC}$ or GND		3.6V			±5	
	$V_{\rm I} = 0.7 V$	2.3V	45			-	
	$V_{\rm I} = 1.7 V$		-45				
$I_{\rm I} ({\rm Hold})^{(3)}$	$V_{\rm I} = 0.8 V$	2.017	75				
	$V_{\rm I} = 2.0 \rm V$	3.0V	-75			μΑ	
	$V_{\rm I} = 0$ to 3.6V	3.6V			±500		
$I_{OZ}^{(4)}$	$V_{O} = V_{CC}$ or GND	3.6V			±10		
I _{CC}	$V_{\rm I} = V_{\rm CC} \text{ or GND}$ $I_{\rm O} = 0$		3.6V			40	
ΔI_{CC}	One input at V _{CC} - 0.6V, Other inpu	3V to 3.6V			750		
C _I Control Inputs	$V_{I} = V_{CC}$ or GND	3.3V		4		pF	
C _{IO} A or B ports	$V_{O} = V_{CC}$ or GND		3.3V		8		pF

Notes:

- 1. For Max. or Min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device type.
- 2. Typical values are at $V_{CC} = 3.3V$, $+25^{\circ}C$ ambient and maximum loading.
- 3. Bus Hold maximum dynamic current required to switch the input from one state to another.
- 4. For I/O ports, the I_{OZ} includes the input leakage current.



Timing Requirements over Operating Range

Damamatans	Description	Conditions (1)	V_{CC} = 2.5 $V \pm 0.2V$		$V_{CC} = 2.7V$		$V_{CC} = 3.3V \pm 0.3V$		Units
Parameters	Description		Min.	Max.	Min.	Max.	Min.	Max.	Units
fCLOCK	Clock frequency		0	150	0	150	0	150	MHz
tw Pulse	LE high		3.3		3.3		3.3		
Duration	CLK high or low		3.3		3.3		3.3		
	Data before $\overline{\text{CLK}} \downarrow$		1.7		1.4		1.3		
t _{SU} Setup time	Data before LE ↓, CLK high	$C_L = 50 pF$	1.1		1.0		1.0		ns
	Data before LE \(\dslant \), \(\overline{CLK} \) low	$R_L = 500\Omega$	1.9		1.6		1.4		
	Data after CLK ↑		1.7		1.6		1.3		
t _H Hold time	Data after LE \downarrow $\overline{\text{CLK}}$ high		2.0		1.8		1.5		
	Data after LE ↓ CLK low		1.6		1.5		1.2		
$\Delta t/\Delta v^{(2)}$	Input Transition Rise or Fall		0	10	0	10	0	10	ns/V

Notes:

- 1. See test circuit and waveforms.
- 2. Unused control inputs must be held HIGH or LOW to prevent them from floating.

Switching Characteristics Over Operating Range⁽¹⁾

Da wa ma a ta wa	From To		Conditions (1)	$V_{CC} = 2.5V \pm 0.2V$		V _{CC} = 2.7V		$V_{CC} = 3.3V \pm 0.V$		TI*4																		
Parameters	(Input)	nput) (Output)	Conditions	Min. ⁽²⁾	Max.	Min. ⁽²⁾	Max.	Min. ⁽²⁾	Max.	Units																		
f_{MAX}				150		150		150		MHz																		
	A or B	B or A	$C_L = 50 pF$ $R_L = 500 \Omega$				5.1		4.7	1	3.9																	
t_{PD}	LE	A or B			5.9		5.5	1.3	4.7																			
	CLK	A or B				$C_L = 50 pF$	$C_L = 50 pF$	$C_L = 50 pF$	$C_L = 50 pF$	$C_L = 50pF$	$C_L = 50 pF$		6.6		6.6	1.1	5.5											
$t_{\rm EN}$	OEAB	В				1.0	5.7		5.4	1.0	4.6	ns																
$t_{ m DIS}$	OEAB	В					6.1		5.7	1.5	5.0																	
t _{EN}	ŌEBA	A					6.2		6.2	1.0	5.2																	
t _{DIS}	OEBA	A			5.4		4.6	1.0	4.3																			

Notes:

- 1. See test circuit and waveforms.
- 2. Minimum limits are guaranteed but not tested on Propagation Delays.

Operating Characteristics, $T_A = 25^{\circ}C$

Paramete		Test Conditions	$V_{\rm CC} = 2.5 V \pm 0.2 V$	$V_{CC} = 3.3V \pm 0.3V$	Units
rarameter		Test Conditions	Турі	Cints	
C _{PD} Power Dissipation	Outputs Enabled	$C_{\rm L} = 50 {\rm pF}$	40	51	рF
Capacitance	Outputs Disabled	f = 10 MHz	6	6	pr

Pericom Semiconductor Corporation

2380 Bering Drive • San Jose, CA 95131 • 1-800-435-2336 • Fax (408) 435-1100 • http://www.pericom.com