

UHF Female to BNC Male Adapter



PE9107

TECHNICAL DATA SHEET

Configuration	
Connector 1	UHF Female
Impedance 1	50 Ohms
Connector 2	BNC Male
Impedance 2	50 Ohms
Adapter Design	Standard
Body Style	Straight
lechanical Specifications	
Size	
Length, in [mm]	1.294 [32.87]
Width/Dia., in [mm]	0.625 [15.88]
Connector 1	
Type	UHF Female
Inner Conductor Material and Plating	Gold
Body Material and Plating	Brass, Nickel
Dielectric Type	PTFE
Connector 2	
Туре	BNC Male
Inner Conductor Material and Plating	Gold
Coupling Nut Material and Plating	Brass, Nickel
Body Material and Plating	Brass, Nickel
Dielectric Type	PTFE
compliance Certifications (visit www.Pasternack.com fo	or current document)
RoHS Compliant	Yes
Rons Compliant	Tes
Plotted and Other Data	
Notes:	Values at 25 °C, sea level
	es has same day shipment for domestic and International orde availability and are part of the broadest selection in the industr
Click the following link (or enter part number in "SEARCH" on nventory and certifications: UHF Female to BNC Male Adapt	on website) to obtain additional part information including price er PE9107
	ht-adapter-pe9107-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com

PE9107 CAD Drawing

UHF Female to BNC Male Adapter

