





### **SWITCHING Diodes**

#### Applications

High speed switching

#### Features

- 1) Extremely small surface mounting type.
- 2) High Speed.
- 3) High reliability.
- Construction

Silicon epitaxial planar

# Pb-Free package is available

RoHS product for packing code suffix "G" Halogen free product for packing code suffix "H" Moisture Sensitivity Level 1

Marking code: 3'cf'+

**SOD-923** 



Dimensions in inches and (millimeters)

# Maximum Ratings and Electrical Characteristics, Single Diode @T<sub>A</sub>=25

Parameter		Limits	Unit
Peak reverse voltage	V <sub>RM</sub>	90	V
DC reverse voltage	$V_{R}$	80	V
Peak forward current	I <sub>FM</sub>	225	mA
Mean rectifying current	Io	100	mA
Surge current (1s)	I <sub>surge</sub>	500	mA
Junction temperature	Tj	125	
Operating/Storage temperature	T <sub>stg</sub>	-55~+125	

#### Electrical Ratings @T<sub>A</sub>=25

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Forward voltage	V <sub>F</sub>			1.2	<b>V</b>	I <sub>F</sub> =100mA
Reverse current	I <sub>R</sub>			0.1	μА	V <sub>R</sub> =80V
Capacitance between terminals	C <sub>T</sub>			3.0	рF	V <sub>R</sub> =0.5V,f=1MHZ
Reverse recovery time	t <sub>rr</sub>			4	ns	V <sub>R</sub> =6V,I <sub>F</sub> =10mA,R <sub>L</sub> =100

# 1SS400CST5



#### **ELECTRICAL CHARACTERISTIC CURVES**

 $(Ta = 25^{\circ}C)$ 




Fig.1 Forward characteristics




Fig.3 Capacitance between terminals




Fig.5 Surge current characteristics




Fig.2 Reverse characteristics




Fig.4 Reverse recovery time characteristics




Fig.6 Reverse recovery time (t<sub>rr</sub>) measurement circuit





# **Ordering Information:**

Device PN	Packing				
1SS400CST5G <sup>(1)</sup> -WS	Tape&Reel: 8 Kpcs/Reel				

Note: (1) RoHS product for packing code suffix "G"; Halogen free product for packing code suffix "H"

#### \*\*\*Disclaimer\*\*\*

WILLAS reserves the right to make changes without notice to any product specification herein, to make corrections, modifications, enhancements or other changes. WILLAS or anyone on its behalf assumes no responsibility or liability for any errors or inaccuracies. Data sheet specifications and its information contained are intended to provide a product description only. "Typical" parameters which may be included on WILLAS data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. WILLAS does not assume any liability arising out of the application or use of any product or circuit.

WILLAS products are not designed, intended or authorized for use in medical, life-saving implant or other applications intended for life-sustaining or other related applications where a failure or malfunction of component or circuitry may directly or indirectly cause injury or threaten a life without expressed written approval of WILLAS. Customers using or selling WILLAS components for use in such applications do so at their own risk and shall agree to fully indemnify WILLAS Inc and its subsidiaries harmless against all claims, damages and expenditures.