

# 75 Ohm BNC Male to BNC Female Right Angle Adapter



## **TECHNICAL DATA SHEET**

PE9361

## 75 Ohm BNC Male to BNC Female Right Angle Adapter

### Configuration

Connector 1 BNC Male
Impedance 1 75 Ohms
Connector 2 BNC Female
Impedance 2 75 Ohms
Adapter Design Standard
Body Style Right Angle

## **Mechanical Specifications**

#### Size

 Length, in [mm]
 1.03 [26.16]

 Width/Dia., in [mm]
 0.57 [14.48]

 Height, in [mm]
 0.875 [22.23]

#### **Connector 1**

Type BNC Male
Inner Conductor Material and Plating Gold
Coupling Nut Material and Plating Brass, Nickel
Body Material and Plating Brass, Nickel
Dielectric Type PTFE

### Connector 2

Type BNC Female
Inner Conductor Material and Plating Gold
Body Material and Plating Brass, Nickel
Dielectric Type PTFE

## Compliance Certifications (visit www.Pasternack.com for current document)

RoHS Compliant Yes

## **Plotted and Other Data**

Notes: Values at 25 °C, sea level

URL: http://www.pasternack.com/bnc-male-bnc-female-right-angle-adapter-pe9361-p.aspx

75 Ohm BNC Male to BNC Female Right Angle Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.



Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623

**PE9361 CAD Drawing**75 Ohm BNC Male to BNC Female Right Angle Adapter

