



#### **Description**

The OX-202 is part of a series of oscillators specifically designed to support Timing Over Packet applications, in particular 1588-2008 based frequency and phase reference systems. The OX-202 is stratum 3E compliant.

#### **Features**

- Available in three standard frequencies (10MHz, 12.8MHz and 20MHz)
- Excellent temperature stability
- Superior long term stability
- Optimized to support Timing Over Packet applications
- Stratum 3E compliant according to GR1244

## **Applications**

- SETS clock support
- Wireless Base Stations
- Edge and Core Routers


### **Performance Specifications**


Frequency Stability <sup>1</sup>					
Parameter	Min	Тур	Max	Units	Notes
Over all stability (df/f <sub>0</sub> )			±2.6	ppm	Free run accuracy (20 years)
Drift			±1	ppb	Over 24 hours and ±3.0°C
Temperature stability (df/f)			10	ppb pk -pk	-40 to 85°C
Initial Tolerance (df/f <sub>0</sub> )			±0.5	ppm	@25℃
vs. supply voltage change (df/f)			±2	ppb	static; 3.3V ± 1%
vs. load change (df/f)			±5	ppb	static; Load ± 5%
vs. aging / daily (df/f)			±0.75	ppb	after 7 days; @25°C
vs. aging / month (df/f)			±25	ppb	after 7days; @25ºC
vs. aging / year (df/f)			±100	ppb	after 7 days; @25°C
vs. aging / 20 years (df/f)			±2.0	ppm	after 7 days; @25°C
Phase Stability					
Parameter	Min	Тур	Max	Units	Notes
Jitter			1	ps rms	@12kHz to 20MHz
MTIE 1s		0.2		ns	Wander Generation per GR1244, system performance when locked through a 1mHz loop bandwidth, see typical performance data.
MTIE 10s		1.6		ns	
MTIE 100s		12		ns	
MTIE 1000s		34		ns	

# **Performance Specifications**

	Phase Stability (continued)					
Parameter	Min	Тур	Max	Units	Notes	
TDEV 1s		0.01		ns	Wander Generation per GR1244, system	
TDEV 10s		0.05		ns	performance when locked through a 1mHz loop bandwidth, see typical perfor-	
TDEV 100s		0.8		ns	mance data.	
TDEV 1000s		3.5		ns		
Phase Noise						
Parameter	Min	Тур	Max	Units	Notes	
Phase Noise at 1 Hz Offset			-85	dBc/Hz		
Phase Noise at 10 Hz Offset			-115	dBc/Hz		
Phase Noise at 100 Hz Offset			-135	dBc/Hz		
Phase Noise 1 kHz Offset			-145	dBc/Hz		
Phase Noise at 10 kHz Offset			-150	dBc/Hz		
Phase Noise at 100kHz Offset			-150	dBc/Hz		
		F	RF Output			
Signal		HCMOS				
Load		15			±10%	
Rise Time	<10			ns	@ 10% to 90% V <sub>out</sub>	
Fall Time	<10			ns	@90% to 10% V <sub>out</sub>	
Duty Cycle	45/55			%	@ 50% V <sub>out</sub>	
V Low	0.4			V	With V <sub>s</sub> 3.0V and 15pF load	
V High	2.4			V	With V <sub>s</sub> 3.0V and 15pF load	
V Low		0.5			With V <sub>s</sub> 5.0V and 15pF load	
V High		3.5			With $V_s$ 5.0V and 15pF load	
			Supply			
Supply Voltage (V <sub>s</sub> )		3.3, 5.0		V	±10%	
Power consumption	<1.5			W	Steady state, @ V <sub>s</sub> = 3.3V, 25°C	
Power consumption	<3.3			W	During warm up, @ $V_s = 3.3V$ , 25°C	
		Additio	onal Parame	ters		
Warm Up Time	3			minutes	@25°C to final frequency (1 Hour) within ±0.1ppm	
ROHS	ROHS 6 com	ROHS 6 compliant				
Washable	Washable de	Washable device (hermetically sealed).				
		Absolute	Maximum R	atings		
	Min		Max	Units		
Operating temperature range	-40			85	°C	
Storage temperature range		-50		90	°C	


# **Typical Performance**





Wander Generation per GR1244, system performance when locked through a 1mHz loop bandwidth.

### **Outline Drawing / Enclosure**




#### Dimensions in mm

Height Codes					
Code	Height "H"	Pin Length "L"			
2	13.4	6.35			

Pin Assignment				
Pin	Connection			
1	RF Out			
2	Ground (case)			
3	NC			
4	NC			
5	Supply Voltage Input (V <sub>s</sub> )			

### **Ordering Information**



#### **Notes:**

- 1. Contact factory for improved stabilities or additional product options. Not all options and codes are available at all frequencies.
- 2. Unless other stated all values are valid after warm-up time and refer to typical conditions for supply voltage, frequency control voltage, load, temperature (25°C).
- 3. Phase noise degrades with increasing output frequency.
- 4. Subject to technical modification.
- 5. Contact factory for availability.



Vectron International reserves the right to make changes to the product(s) and or information contained herein without notice. No liability is assumed as a result of their use or application. No rights under any patent accompany the sale of any such product(s) or information.

Rev: 2-18-2014 jar