

Pb

**Micro Commercial Components** 

Micro Commercial Components 20736 Marilla Street Chatsworth CA 91311

Phone:(818) 701-4933 Fax: (818) 701-4939

# MMS9015-L MMS9015-H

# **Features**

- Halogen free available upon request by adding suffix "-HF"
- SOT-23 Plastic-Encapsulate Transistors
- Capable of 0.2Watts(Tamb=25°C) of Power Dissipation.
- Collector-current 0.1A
- Collector-base Voltage 50V
- Operating and storage junction temperature range: -55°C to +150°C
- Marking: M6
- Lead Free Finish/RoHS Compliant ("P" Suffix designates RoHS Compliant. See ordering information)
- Epoxy meets UL 94 V-0 flammability rating
- Moisure Sensitivity Level 1

# **Electrical Characteristics @ 25°C Unless Otherwise Specified**

Symbol	Parameter	Min	Max	Units
OFF CHARAC	CTERISTICS			
$V_{(BR)CBO}$	Collector-Base Breakdown Voltage	50		Vdc
	(l <sub>c</sub> =100µAdc, l <sub>∈</sub> =0)			
$V_{(BR)CEO}$	Collector-Emitter Breakdown Voltage	45		Vdc
	(l <sub>c</sub> =1.0mAdc, l <sub>в</sub> =0)			
$V_{(BR)EBO}$	Emitter-Base Breakdown Voltage	5.0		Vdc
	(l <sub>=</sub> =100µAdc, l <sub>C</sub> =0)			
Сво	Collector Cutoff Current 0.1		μAdc	
	(V <sub>CB</sub> =50Vdc, <u></u>			
I <sub>EBO</sub>	Emitter Cutoff Current		0.1	μAdc
	(V <sub>EB</sub> =5.0Vdc,			*

ON CHARACTERISTICS	
--------------------	--

h <sub>FE(1)</sub>	DC Current Gain	200	1000	
	(l <sub>c</sub> =1.0mAdc, V <sub>CE</sub> =5.0Vdc)			
$V_{CE(sat)}$	Collector-Emitter Saturation Voltage		0.3	Vdc
(,	(b=100mAdc, b=10mAdc)			
$V_{BE(sat)}$	V <sub>BE(sat)</sub> Base-Emitter Saturation Voltage		1.0	Vdc
, , , ,	(L=100mAdc, L=10mAdc)			


# **SMALL-SIGNAL CHARACTERISTICS**


1	f <sub>T</sub>	Transistor Frequency		 MHz
		( $l_c$ =10mAdc, $V_{ce}$ =5.0Vdc, f=30MHz)		

#### **CLASSIFICATION OF HFE**

Rank	L	Н
Range	200~450	450~1000


# PNP Silicon Plastic-Encapsulate Transistor





DIMENSIONS					
	INCHES		MM		
DIM	MIN	MAX	MIN	MAX	NOTE
Α	.110	.120	2.80	3.04	
В	.083	.104	2.10	2.64	
O	.047	.055	1.20	1.40	
D	.035	.041	.89	1.03	
Е	.070	.081	1.78	2.05	
F	.018	.024	.45	.60	
Ð	.0005	.0039	.013	.100	
Η	.035	.044	.89	1.12	
J	.003	.007	.085	.180	
K	.015	.020	.37	.51	

### Suggested Solder Pad Layout





#### Micro Commercial Components

## **Ordering Information:**

Device	Packing
Part Number-TP	Tape&Reel 3Kpcs/Reel

Note: Adding "-HF" suffix for halogen free, eg. Part Number-TP-HF

#### \*\*\*IMPORTANT NOTICE\*\*\*

Micro Commercial Components Corp. reserves the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes. *Micro Commercial Components* Corp. does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights ,nor the rights of others . The user of products in such applications shall assume all risks of such use and will agree to hold *Micro Commercial Components Corp* . and all the companies whose products are represented on our website, harmless against all damages.

#### \*\*\*LIFE SUPPORT\*\*\*

MCC's products are not authorized for use as critical components in life support devices or systems without the express written approval of Micro Commercial Components Corporation.

#### \*\*\*CUSTOMER AWARENESS\*\*\*

Counterfeiting of semiconductor parts is a growing problem in the industry. Micro Commercial Components (MCC) is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. MCC strongly encourages customers to purchase MCC parts either directly from MCC or from Authorized MCC Distributors who are listed by country on our web page cited below. Products customers buy either from MCC directly or from Authorized MCC Distributors are genuine parts, have full traceability, meet MCC's quality standards for handling and storage. MCC will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. MCC is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.