
### **DISCRETE SEMICONDUCTORS**

# DATA SHEET



# **PBSS5140T** 40 V low V<sub>CEsat</sub> PNP transistor

Product specification Supersedes data of 2001 Jul 20 2004 Jan 07





Philips Semiconductors

### 40 V low V<sub>CEsat</sub> PNP transistor

### **PBSS5140T**

### **FEATURES**

- Low collector-emitter saturation voltage
- High current capabilities
- Improved device reliability due to reduced heat generation.

### **APPLICATIONS**

- · General purpose switching and muting
- · LCD back lighting
- Supply line switching circuits
- Battery driven equipment (mobile phones, video cameras and hand-held devices).

### **DESCRIPTION**

PNP low V<sub>CEsat</sub> transistor in a SOT23 plastic package.

#### **MARKING**

TYPE NUMBER	MARKING CODE(1)
PBSS5140T	p2H*

### Note


- 1. \* = p: made in Hongkong.
  - \* = t: made in Malaysia.
  - \* = W: made in China.

### **QUICK REFERENCE DATA**

SYMBOL	PARAMETER	MAX.	UNIT
V <sub>CEO</sub>	collector-emitter voltage	-40	V
I <sub>CM</sub>	peak collector current	-2	Α
R <sub>CEsat</sub>	equivalent on-resistance	<500	mΩ

### **PINNING**

PIN	DESCRIPTION	
1	base	
2	emitter	
3	collector	



### **ORDERING INFORMATION**

TYPE NUMBER		PACKAGE		
I TPE NOWIBER	NAME DESCRIPTION VERSION			
PBSS5140T	-	plastic surface mounted package; 3 leads	SOT23	

### 40 V low V<sub>CEsat</sub> PNP transistor

PBSS5140T

### **LIMITING VALUES**

In accordance with the Absolute Maximum Rating System (IEC 60134).

SYMBOL	PARAMETER CONDITIONS		MIN.	MAX.	UNIT
V <sub>CBO</sub>	collector-base voltage	open emitter	_	-40	V
V <sub>CEO</sub>	collector-emitter voltage	open base	_	-40	V
V <sub>EBO</sub>	emitter-base voltage	open collector	_	<b>-</b> 5	V
I <sub>C</sub>	collector current (DC)		_	<b>-1</b>	Α
I <sub>CM</sub>	peak collector current		_	-2	А
I <sub>BM</sub>	peak base current		_	-1	Α
P <sub>tot</sub>	total power dissipation	T <sub>amb</sub> ≤ 25 °C; note 1	_	300	mW
		T <sub>amb</sub> ≤ 25 °C; note 2	_	450	mW
T <sub>stg</sub>	storage temperature		-65	+150	°C
Tj	junction temperature		_	150	°C
T <sub>amb</sub>	operating ambient temperature		-65	+150	°C

### **Notes**

- 1. Device mounted on a printed-circuit board, single-sided copper, tinplated and standard footprint.
- 2. Device mounted on a printed-circuit board, single-sided copper, tinplated and mounting pad for collector 1 cm<sup>2</sup>.

### THERMAL CHARACTERISTICS

SYMBOL	OL PARAMETER CONDITIONS		VALUE	UNIT
R <sub>th(j-a)</sub>	thermal resistance from junction to	in free air; note 1	417	K/W
	ambient	in free air; note 2	278	K/W

### Notes

- 1. Device mounted on a printed-circuit board, single-sided copper, tinplated and standard footprint.
- 2. Device mounted on a printed-circuit board, single-sided copper, tinplated and mounting pad for collector 1 cm<sup>2</sup>.

# 40 V low $V_{CEsat}$ PNP transistor

PBSS5140T

### **CHARACTERISTICS**

 $T_{amb}$  = 25 °C unless otherwise specified.


SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
I <sub>CBO</sub>	collector-base cut-off current	$V_{CB} = -40 \text{ V; } I_{C} = 0$	_	_	-100	nA
		$V_{CB} = -40 \text{ V}; I_C = 0; T_j = 150 ^{\circ}\text{C}$	_	_	-50	μΑ
I <sub>CEO</sub>	collector-emitter cut-off current	$V_{CE} = -30 \text{ V}; I_{B} = 0$	_	_	-100	nA
I <sub>EBO</sub>	emitter-base cut-off current	$V_{EB} = -5 \text{ V}; I_C = 0$	_	_	-100	nA
h <sub>FE</sub>	DC current gain	$V_{CE} = -5 \text{ V}; I_{C} = -1 \text{ mA}$	300	_	_	
		$V_{CE} = -5 \text{ V}; I_{C} = -100 \text{ mA}$	300	_	800	
		$V_{CE} = -5 \text{ V}; I_{C} = -500 \text{ mA}$	250	_	_	
		$V_{CE} = -5 \text{ V}; I_{C} = -1 \text{ A}$	160	_	_	
V <sub>CEsat</sub>	collector-emitter saturation	$I_C = -100 \text{ mA}; I_B = -1 \text{ mA}$	_	_	-200	mV
	voltage	$I_C = -500 \text{ mA}; I_B = -50 \text{ mA}$	_	_	-250	mV
		$I_C = -1 \text{ A}; I_B = -100 \text{ mA}$	_	_	-500	mV
R <sub>CEsat</sub>	equivalent on-resistance	$I_C = -500 \text{ mA}$ ; $I_B = -50 \text{ mA}$ ; note 1	_	300	<500	mΩ
V <sub>BEsat</sub>	base-emitter saturation voltage	$I_C = -1 \text{ A}; I_B = -50 \text{ mA}$	_	_	-1.1	V
V <sub>BEon</sub>	base-emitter turn-on voltage	$V_{CE} = -5 \text{ V}; I_{C} = -1 \text{ A}$	_	_	-1	V
f <sub>T</sub>	transition frequency	$I_C = -50 \text{ mA}; V_{CE} = -10 \text{ V};$ f = 100 MHz	150	_	_	MHz
C <sub>c</sub>	collector capacitance	$V_{CB} = -10 \text{ V}; I_E = I_e = 0; f = 1 \text{ MHz}$	-	_	12	pF

### Note

1. Pulse test:  $t_p \le 300~\mu s;~\delta \le 0.02.$ 

### 40 V low V<sub>CEsat</sub> PNP transistor


### PBSS5140T



 $V_{CE} = -5 \text{ V}.$ 

- (1) T<sub>amb</sub> = 150 °C.
- (2)  $T_{amb} = 25 \, ^{\circ}C$ .
- (3)  $T_{amb} = -55 \, ^{\circ}C$ .


Fig.2 DC current gain as a function of collector current; typical values.



 $V_{CE} = -5 \text{ V}.$ 

- (1)  $T_{amb} = -55 \, ^{\circ}C$ .
- (2)  $T_{amb} = 25 \, ^{\circ}C$ .
- (3)  $T_{amb} = 150 \, ^{\circ}C$ .


Fig.3 Base-emitter voltage as a function of collector current; typical values.



 $I_{\rm C}/I_{\rm B} = 10.$ 

- (1)  $T_{amb} = 150 \, ^{\circ}C$ .
- (2) T<sub>amb</sub> = 25 °C.
- (3)  $T_{amb} = -55 \, ^{\circ}C$ .

Fig.4 Collector-emitter saturation voltage as a function of collector current; typical values.



 $I_{\rm C}/I_{\rm B} = 10$ .

5


- (1)  $T_{amb} = 150 \, ^{\circ}C$ .
- (2)  $T_{amb} = 25 \, ^{\circ}C$ .
- (3)  $T_{amb} = -55 \, ^{\circ}C$ .

Fig.5 Equivalent on-resistance as a function of collector current; typical values.

2004 Jan 07

# 40 V low $V_{CEsat}$ PNP transistor

PBSS5140T



 $V_{CE} = -10 \text{ V}.$ 

- (1)  $T_{amb} = 150 \, ^{\circ}C$ .
- (2)  $T_{amb} = 25 \, ^{\circ}C$ .
- (3)  $T_{amb} = -55 \, ^{\circ}C$ .

Fig.6 Transition frequency as a function of collector current; typical values.


## 40 V low $V_{CEsat}$ PNP transistor

PBSS5140T

### **PACKAGE OUTLINE**

### Plastic surface mounted package; 3 leads

SOT23



OUTLINE	REFERENCES			EUROPEAN	ISSUE DATE	
VERSION	IEC	JEDEC	EIAJ		PROJECTION	ISSUE DATE
SOT23		TO-236AB				<del>-97-02-28-</del> 99-09-13

### 40 V low V<sub>CEsat</sub> PNP transistor

**PBSS5140T** 

### **DATA SHEET STATUS**

LEVEL	DATA SHEET STATUS <sup>(1)</sup>	PRODUCT STATUS(2)(3)	DEFINITION
I	Objective data	Development	This data sheet contains data from the objective specification for product development. Philips Semiconductors reserves the right to change the specification in any manner without notice.
II	Preliminary data	Qualification	This data sheet contains data from the preliminary specification. Supplementary data will be published at a later date. Philips Semiconductors reserves the right to change the specification without notice, in order to improve the design and supply the best possible product.
III	Product data	Production	This data sheet contains data from the product specification. Philips Semiconductors reserves the right to make changes at any time in order to improve the design, manufacturing and supply. Relevant changes will be communicated via a Customer Product/Process Change Notification (CPCN).

#### **Notes**

- 1. Please consult the most recently issued data sheet before initiating or completing a design.
- 2. The product status of the device(s) described in this data sheet may have changed since this data sheet was published. The latest information is available on the Internet at URL http://www.semiconductors.philips.com.
- 3. For data sheets describing multiple type numbers, the highest-level product status determines the data sheet status.

### **DEFINITIONS**

**Short-form specification** — The data in a short-form specification is extracted from a full data sheet with the same type number and title. For detailed information see the relevant data sheet or data handbook.

Limiting values definition — Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 60134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.

Application information — Applications that are described herein for any of these products are for illustrative purposes only. Philips Semiconductors make no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

#### **DISCLAIMERS**

Life support applications — These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips Semiconductors customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips Semiconductors for any damages resulting from such application.

Right to make changes — Philips Semiconductors reserves the right to make changes in the products - including circuits, standard cells, and/or software - described or contained herein in order to improve design and/or performance. When the product is in full production (status 'Production'), relevant changes will be communicated via a Customer Product/Process Change Notification (CPCN). Philips Semiconductors assumes no responsibility or liability for the use of any of these products, conveys no licence or title under any patent, copyright, or mask work right to these products, and makes no representations or warranties that these products are free from patent, copyright, or mask work right infringement, unless otherwise specified.

# Philips Semiconductors – a worldwide company

#### **Contact information**

For additional information please visit http://www.semiconductors.philips.com. Fax: +31 40 27 24825 For sales offices addresses send e-mail to: sales.addresses@www.semiconductors.philips.com.

© Koninklijke Philips Electronics N.V. 2004

SCA76

All rights are reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner.

The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Printed in The Netherlands

R75/03/pp9

Date of release: 2004 Jan 07

Document order number: 9397 750 12438

Let's make things better.

Philips Semiconductors



