


25A AUTOMOTIVE BUTTON DIODE

Features

- Diffused Junction
- Low Leakage
- Low Cost
- High Surge Current Capability
- Low Cost Construction Utilizing Void-Free Molded Plastic Technique



Mechanical Data

- Case: AR or ARS, Molded Plastic
- Terminals: Plated Terminals Solderable per MIL-STD-202, Method 208
- Polarity: Color Ring Denotes Cathode End
- Weight: 1.8 grams (approx.)Mounting Position: Any
- Marking: Color Ring Only
- Lead Free: For RoHS / Lead Free Version,
 Add "-LF" Suffix to Part Number, See Page 3

	Α	R	ARS			
Dim	Min	Max	Min	Max		
Α	9.70	10.40	8.30	8.90		
В	5.50	5.70	5.50	5.70		
С	6.0	6.40	6.0	6.40		
D	4.2	4.7	4.2	4.7		
All Dimensions in mm						

Maximum Ratings and Electrical Characteristics @T_A=25°C unless otherwise specified

Single Phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.

Characteristic	Symbol	AR/S 25A	AR/S 25B	AR/S 25D	AR/S 25G	AR/S 25J	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	VRRM VRWM VR	50	100	200	400	600	V
RMS Reverse Voltage	VR(RMS)	35	70	140	280	420	V
Average Rectified Output Current @T _C = 150°C	lo	25				Α	
Non-Repetitive Peak Forward Surge Current 8.3ms Single half sine-wave superimposed on rated load (JEDEC Method) at T _J = 150°C	İFSM	400				А	
Forward Voltage $@I_F = 25A$	VFM	/FM 1.0			V		
	IRM	5.0 250				μΑ	
Reverse Recovery Time (Note 1)	trr	3.0				μS	
Typical Junction Capacitance (Note 2)	Cj	300				pF	
Typical Thermal Resistance (Note 3)	R⊕JC	1.0			°C/W		
Operating and Storage Temperature Range	Тл, Тѕтс	-50 to +175			°C		
Polarity and Voltage Denotation Color Ring		Green	Yellow	Silver	Orange	Red	

Note: 1. Measured with $I_F = 0.5A$, $I_R = 1.0A$, $I_{RR} = 0.25A$

- 2. Measured at 1.0 MHz and applied reverse voltage of 4.0V D.C.
- 3. Thermal Resistance: Junction to case, single side cooled.





Fig. 1 Forward Current Derating Curve



 $V_{\rm F}$, INSTANTANEOUS FORWARD VOLTAGE (V)

Fig. 2 Typical Forward Characteristics




Fig. 3 Max Non-Repetitive Peak Fwd Surge Current




Fig. 4 Typical Junction Capacitance

ORDERING INFORMATION

Product No.	Package Type	Shipping Quantity			
AR25A	10mm Button	1000 Units/Box			
ARS25A	8.6mm Button	1000 Units/Box			
AR25B	10mm Button	1000 Units/Box			
ARS25B	8.6mm Button	1000 Units/Box			
AR25D	10mm Button	1000 Units/Box			
ARS25D	8.6mm Button	1000 Units/Box			
AR25G	10mm Button	1000 Units/Box			
ARS25G	8.6mm Button	1000 Units/Box			
AR25J	10mm Button	1000 Units/Box			
ARS25J	8.6mm Button	1000 Units/Box			

- Shipping quantity given is for minimum packing quantity only. For minimum order quantity, please consult the Sales Department.
- To order Lead Free version (with Lead Free finish), add "-LF" suffix to part number above. For example, AR25A-LF.

Won-Top Electronics Co., Ltd (WTE) has checked all information carefully and believes it to be correct and accurate. However, WTE cannot assume any responsibility for inaccuracies. Furthermore, this information does not give the purchaser of semiconductor devices any license under patent rights to manufacturer. WTE reserves the right to change any or all information herein without further notice.

WARNING: DO NOT USE IN LIFE SUPPORT EQUIPMENT. WTE power semiconductor products are not authorized for use as critical components in life support devices or systems without the express written approval.

Won-Top Electronics Co., Ltd.

No. 44 Yu Kang North 3rd Road, Chine Chen Dist., Kaohsiung, Taiwan

Phone: 886-7-822-5408 or 886-7-822-5410

Fax: 886-7-822-5417 Email: sales@wontop.com Internet: http://www.wontop.com

We power your everyday.