TECHNICAL DATA DATA SHEET 4683, REV. -

HERMETIC POWER SCHOTTKY RECTIFIER Low Forward Voltage

Applications:

• Switching Power Supply • Converters • Free-Wheeling Diodes • Polarity Protection Diode

Features:

- Soft Reverse Recovery at Low and High Temperature
- Low Forward Voltage Drop
- Low Power Loss, High Efficiency
- High Surge Capacity
- Guard Ring for Enhanced Durability and Long Term Reliability
- Guaranteed Reverse Avalanche Characteristics

Maximum Ratings:


Characteristics	Symbol	Condition	Max.	Units
Peak Inverse Voltage	V _{RWM}	-	100	V
Max. Average Forward Current	I _{F(AV)}	50% duty cycle, rectangular wave form (Single/Doubler)	15	A
Max. Average Forward Current	I _{F(AV)}	50% duty cycle, rectangular wave form (Common Cathode/Common Anode)	30	A
Max. Peak One Cycle Non- Repetitive Surge Current	I _{FSM}	8.3 ms, half Sine wave (per leg)	200	A
Max. Thermal Resistance	$R_{ ext{ heta}JC}$	(Single)	1.45	°C/W
Max. Thermal Resistance	$R_{ ext{ heta}JC}$	(Common Cathode/Common Anode/Doubler) (per leg)	0.72	°C/W
Max. Junction Temperature	ΤJ	-	-65 to +200	°C
Max. Storage Temperature	T _{stg}	-	-65 to +200	°C


Electrical Characteristics:

Characteristics	Symbol	Condition	Max.	Units
Max. Forward Voltage Drop	V_{F1}	@ 15A, Pulse, T _J = 25 °C	0.93	V
		(per leg)		
	V _{F2}	@ 15A, Pulse, T _J = 125 °C	0.77	V
		(per leg)		
Max. Reverse Current	I _{R1}	@V _R = 100V, Pulse,	0.35	mA
		$T_J = 25 \ ^{\circ}C \ (per \ leg)$		
	I _{R2}	@V _R = 100V, Pulse,	8	mA
		$T_J = 125 \ ^{\circ}C \ (per \ leg)$		
Max. Junction Capacitance	Ст	@V _R = 5V, T _C = 25 °C	500	pF
		f _{SIG} = 1MHz,		
		$V_{SIG} = 50 \text{mV} (p-p) (per leg)$		

• 221 WEST INDUSTRY COURT • DEER PARK, NY 11729-4681 • PHONE (631) 586-7600 • FAX (631) 242-9798 • • World Wide Web - http://www.sensitron.com • E-mail Address - sales@sensitron.com •

TECHNICAL DATA DATA SHEET 4683, REV. -






TO-258

PINOUT TABLE

PIN 1	PIN 2	PIN 3
CATHODE	ANODE	ANODE
ANODE 1	COMMON CATHODE	ANODE 2
CATHODE 1	COMMON ANODE	CATHODE 2
ANODE	CATHODE/ANODE	CATHODE
	CATHODE ANODE 1 CATHODE 1	CATHODEANODEANODE 1COMMON CATHODECATHODE 1COMMON ANODE

Note: The V_f curves shown are for the SD125SC100 un-packaged die only.



Typical Reverse Characteristics

• 221 WEST INDUSTRY COURT • DEER PARK, NY 11729-4681 • PHONE (631) 586-7600 • FAX (631) 242-9798 • World Wide Web - http://www.sensitron.com • E-mail Address - sales@sensitron.com •



TECHNICAL DATA

DISCLAIMER:

1- The information given herein, including the specifications and dimensions, is subject to change without prior notice to improve product characteristics. Before ordering, purchasers are advised to contact the Sensitron Semiconductor sales department for the latest version of the datasheet(s).

2- In cases where extremely high reliability is required (such as use in nuclear power control, aerospace and aviation, traffic equipment, medical equipment, and safety equipment), safety should be ensured by using semiconductor devices that feature assured safety or by means of users' fail-safe precautions or other arrangement.

3- In no event shall Sensitron Semiconductor be liable for any damages that may result from an accident or any other cause during operation of the user's units according to the datasheet(s). Sensitron Semiconductor assumes no responsibility for any intellectual property claims or any other problems that may result from applications of information, products or circuits described in the datasheets.
4- In no event shall Sensitron Semiconductor be liable for any failure in a semiconductor device or any secondary damage resulting from use at a value exceeding the absolute maximum rating.

5- No license is granted by the datasheet(s) under any patents or other rights of any third party or Sensitron Semiconductor.
6- The datasheet(s) may not be reproduced or duplicated, in any form, in whole or part, without the expressed written permission of Sensitron Semiconductor.

7- The products (technologies) described in the datasheet(s) are not to be provided to any party whose purpose in their application will hinder maintenance of international peace and safety nor are they to be applied to that purpose by their direct purchasers or any third party. When exporting these products (technologies), the necessary procedures are to be taken in accordance with related laws and regulations.