CFPS-53, -54, -55, -56 SMD CLOCK OSCILLATORS



ISSUE 4; 6 JANUARY 2009 - RoHS 2002/95/EC

Description

 Surface mount oscillators in a ceramic package with a hermetically sealed metal lid available in a range of voltages

Fast Make Capability

 Please see CFPP-54, -56, -58 series Programmable Oscillators for nearest equivalent fast make parts

Package Outline

■ 2.5 x 2mm

Frequency Range

0.75 to 50MHz

Output Compatibility & Load

- Tri-state CMOS
- Drive Capability 15pF max

Frequency Stabilities

 ±30ppm, ±50ppm, ±100ppm (inclusive of supply voltage output load variations over the operating temperature range)

Operating Temperature Ranges

- -20 to 70°C (CFPS-53, -54, -55, -56)
- -40 to 85°C (CFPS-53I, -54I, -55I, 56I)

Storage Temperature Range

■ -55 to 100°C

Tri-state Operation

- Logic '1' (>80%Vs) to pad 1 enables oscillator output
- Logic '0' (<20% Vs) to pad 1 disables oscillator output; when disabled the oscillator output goes to the high impedance state
- No connection to pad 1 enables oscillator output

Supply Voltage

- 1.8V CFPS-53
- 2.5V CFPS-54
- 3.0V CFPS-55
- 3.3V CFPS-56

Phase Jitter - examples:

- 12.0MHz 0.27ps rms (12kHz 5MHz) typical
- 22.50MHz 0.46ps rms (12kHz 10MHz) typical
- 40.0MHz 0.38ps rms (12kHz 20MHz) typical

Environmental

- Drop: free fall from 100cm, 3 times onto hard wooden surface
- Vibration: 10-36Hz, 1.5mm amplitude, 36-55Hz, 4G sweep time 1min/oct, duration 2hrs for each X, Y & Z axes

Marking Includes

Frequency

Packaging

Bulk or Tape and Reel

Minimum Order Information Required

 Frequency + Model Number + Operating Temperature Code + Frequency Stability



Outline (mm)





Pad Connections
1. Enable/Disable

- 2 GND
- 3. Output
- 3. Ծանթա 4. +Vs




Solder pad layout






Output Waveform



Test Circuit



* Inclusive of jigging & equipment capacitance




Electrical Specifications - maximum limiting values

| Frequency Range | Frequency Stability | Supply Voltage | Supply Current | Rise Time (tr) | Fall Time (tf) | Duty Cycle | Model Number |
|------------------|----------------------------|----------------|----------------|----------------|----------------|------------|---------------------|
| 0.75 to <20.0MHz | ±30ppm, ±50ppm, ±100ppm | 1.8V ±5% | 2.5mA | 10ns | 10ns | 45/55% | CFPS-53 CFPS-53I |
| 20. to <40.0MHz | | | 3.0mA | | | | |
| 40. to 50.0MHz | | | 3.5mA | | | | |
| 0.75 to <20.0MHz | | 2.5V ±5% | 4.5mA | | | 40/60% | CFPS-54 CFPS-54I |
| 20. to <40.0MHz | | | 5.5mA | | | | |
| 40. to 50.0MHz | | | 6.5mA | | | | |
| 0.75 to <20.0MHz | | 3.0V ±5% | 5.5mA | | | 45/55% | CFPS-55 CFPS-55I |
| 20. to <40.0MHz | | | 6.5mA | | | | |
| 40. to 50.0MHz | | | 7.5mA | | | | |
| 0.75 to <20.0MHz | | 3.3V ±5% | 6.0mA | | | | CFPS-56 CFPS-56I |
| 20. to <40.0MHz | | | 7.0mA | | | | |
| 40. to 50.0MHz | | | 8.0mA | | | | |

Ordering Example
Frequency
Model No.
Operating Temperature Code: I = -40 to 85°C; not applicable for -20 to 70°C
Frequency Stability: H = ±30ppm, B = ±50ppm, C = ±100ppm

Please note that the rise and fall times listed are the maximum values we specify to cover various frequency breaks. In practice the actual values are generally lower depending upon the spot frequency chosen. For typical values please contact our sales office.

Tape (mm)



Reel (mm)

