

Product Features

- Passive Integration on Silicon
- Low Insertion Loss
- High Isolation
- Solder Pad
- Good Balance
- Low Cost
- Pb Free / RoHS Compliant

Application

- Repeater
- Base Station
- RF Sub-Systems



Package: SOIC-8

Description


The 2 way power divider is low loss, high isolation, good matching, and phase $\!\!\!/$ amplitude.

The PD23C2 is a monolithic two-way in phase hybrid junction tuned for the 2200~2400MHz band.

Specifications at 25 ℃

PARAMETER	Units	Min	Тур	Max
Frequency Range	MHz	2200		2400
Insertion Loss	dB		0.3	0.5
Input Return Loss	dB	20	22	
Output Return Loss	dB	20	27	
Isolation	dB	20	27	
Phase difference	Deg.		1	3
Amplitude difference	dB		0.1	0.3
Remarks	MHz		2300	

Block Diagram & Pin Out



Absolute Maximum Ratings

Parameter	Value		
Input Power	2 W		
Operating Temperature	-40 ~ +85 ℃		
Storage Temperature	-65 ~ + 150 ℃		

Tel: 82-31-250-5011rfsales@rfhic.com

All specifications may change without notice.


[•] Version 5.5







Typical Performance Data at 25℃ (SOIC-8 Package)











Package Dimensions (Type: SOIC-8)



Recommended Pattern



Unit: $\frac{\text{mm}}{[\text{inch}]}$ Tolerance: $\pm \frac{0.2}{.008}$

RFHIC Corporation (RFHIC) reserves the right to make changes to any products herein or to discontinue any product at any time without notice. RFHIC do not assume any liability for the suitability of its products for any particular purpose, and disclaims any and all liability, including without limitation consequential or incidental damages. The product specifications herein expressed have been carefully checked and are assumed to be reliable. However, RFHIC disclaims liability for inaccuracies and strongly recommends buyers to verify that the information they are using is current before placing purchase orders. RFHIC products are not intended for use in life support equipment or application where malfunction of the product can be expected to result in personal injury or death. Buyer uses or sells such products for any such unintended or unauthorized application, buyer shall indemnify, protect and hold RFHIC and its directors, officers, stockholders, employees, representatives and distributors harmless against any and all claims arising out of such use. RFHIC's liability under or arising out of damages, claims of whatsoever kind and nature which RFHIC products could cause shall be limited in amount to the net purchase price of the products sold to buyer by RFHIC.

- Tel: 82-31-250-5011

Version 5.5

All specifications may change without notice.

• rfsales@rfhic.com