


KSC2859

Low Frequency Power Amplifier

Complement to KSA1182



1. Base 2. Emitter 3. Collector

NPN Epitaxial Silicon Transistor

Absolute Maximum Ratings T_a =25°C unless otherwise noted


Symbol	Parameter	Value	Units
V _{CBO}	Collector-Base Voltage	35	V
V _{CEO}	Collector-Emitter Voltage	30	V
V _{EBO}	Emitter-Base Voltage	5	V
I _C	Collector Current	500	mA
P _C	Collector Power Dissipation	150	mW
T _J	Junction Temperature	150	°C
T _{STG}	Storage Temperature	-55 ~ 150	°C

Electrical Characteristics T_a =25°C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Тур.	Max.	Units
I _{CEO}	Collector Cut-off Current	V_{CB} =35V, I_{E} =0			0.1	μΑ
I _{EBO}	Emitter Cut-off Current	V_{EB} =5V, I_C =0			0.1	μΑ
h _{FE1}	DC Current Gain	V _{CE} =1V, I _C =100mA V _{CE} =6V, I _C =400mA	70 25		240	
V _{CE} (sat)	Collector-Emitter Saturation Voltage	I _C =100mA, I _B =10mA		0.1	0.25	V
V _{BE} (on)	Base-Emitter On Voltage	V _{CE} =1V, I _C =100mA		0.8	1.0	V
f _T	Current Gain-Bandwidth Product	V _{CE} =6V, I _C =20mA		300		MHz
C _{ob}	Output Capacitance	V _{CB} =6V, I _E =0, f=1MHz		7		pF

h_{FE1} Classification

Classification	0	Y	
h _{FE1}	70 ~ 140	120 ~ 240	



Typical Characteristics




Figure 1. Static Characteristics




Figure 2. Base-Emitter On Voltage




Figure 3. DC Current Gain




Figure 4. Output Capacitance






Figure 5. Saturation Voltage


©2002 Fairchild Semiconductor Corporation Rev. A2, September 2002

Package Dimensions

SOT-23







Dimensions in Millimeters

TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™	FACT™	ImpliedDisconnect™	PACMAN™	SPM™
ActiveArray™	FACT Quiet series™	ISOPLANAR™	POP™	Stealth™
Bottomless™	FAST [®]	LittleFET™	Power247™	SuperSOT™-3
CoolFET™	FASTr™	MicroFET™	PowerTrench [®]	SuperSOT™-6
$CROSSVOLT^{TM}$	FRFET™	MicroPak™	QFET™	SuperSOT™-8
DOME™	GlobalOptoisolator™	MICROWIRE™	QS™	SyncFET™
EcoSPARK™	GTO™	MSX™	QT Optoelectronics™	TinyLogic™
E ² CMOS™	HiSeC™	MSXPro™	Quiet Series™	TruTranslation™
EnSigna™	I^2C^{TM}	OCX^{TM}	RapidConfigure™	UHC™
Across the board.	Around the world.™	OCXPro™	RapidConnect™	UltraFET [®]
The Power Franci	hise™	OPTOLOGIC [®]	SILENT SWITCHER®	VCX TM
Programmable Ad	ctive Droop™	OPTOPLANAR™	SMART START™	

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.



Home >> Find products >>

KSC2859

NPN Epitaxial Silicon Transistor

Contents

Features

Qualification Support

- Applications
- Product status/pricing/packaging
- Order Samples

Features

Complement to KSA1182

back to top

Applications

Low Frequency Power Amplifier

back to top

Product status/pricing/packaging

BUY

BUY

Datasheet Download this datasheet



e-mail this datasheet



This page Print version

Related Links

Request samples

How to order products

Product Change Notices (PCNs)

Support

Sales support

Quality and reliability

Design center

Product	Product status	Pb-free Status	Pricing*	Package type	Leads	Packing method	Package Marking Convention**
KSC2859OMTF	Full Production	Full Production	\$0.0316	<u>SOT-23</u>	3	TAPE REEL	<u>Line 1:</u> E1O
KSC2859YMTF	Full Production	Full Production	\$0.0316	<u>SOT-23</u>	3	TAPE REEL	<u>Line 1:</u> E1Y

^{*} Fairchild 1,000 piece Budgetary Pricing

^{**} A sample button will appear if the part is available through Fairchild's on-line samples program. If there is no sample button, please contact a Fairchild distributor to obtain samples



Indicates product with Pb-free second-level interconnect. For more information click here.

Package marking information for product KSC2859 is available. Click here for more information.

back to top

Qualification Support

Click on a product for detailed qualification data

Product
KSC2859OMTF
KSC2859YMTF

back to top

© 2007 Fairchild Semiconductor



Products | Design Center | Support | Company News | Investors | My Fairchild | Contact Us | Site Index | Privacy Policy | Site Terms & Conditions | Standard Terms & Conditions |