
	I	2	3	4		5		6	7		8	
A		nce with HE 507) ERISTICS	CONTACT )	Series - Shell size: <b>EAB</b> (see sheet Front accessory o	<b>c</b>		_13\	N3S5	500G3		te RoHS -	A
в	-ACCESSORIES: I -SHELLS: <u>ELECTRICAL CHARA(</u> -NOMINAL CURRENT: .	BRASS STEEL <u>CTERISTICS</u> 7.5A (SIGNAL CONTACT) 30A or 40A (POWER CONTACT <=7.3 m Ohms(SIGNAL and POWER)	1)	blank:without L :threaded O :threaded V :female s	2) accessory insert M insert L crew UNC	/ 13 UNC 4-40 4-40						В
c	-CONTACT/GROUND :	>=1200 V : >=5000 MOhms RACTERISTICS		Contacts <b>S</b> :Socket Termination type <b>5</b> Right ang Plating <b>00</b> 200 matin	le/Europe gs/unmati	e standard ings					-	c
D	MECHANICAL CHARAC			43 500 matin PCB accessories of A :without H :Metal br G :Metal br M :Metal br	definitio accessory ackets+hc ackets+hc ackets	n(see shee / arpoons for	PCB 2.40m					D
	NOTE ROHS INFORM			Power contacts → 00 :Not fitte 30 :Fitted wi 40 :Fitted wi	d with p th power	c o n t a c t s	30 Amp.	contacts alway	s fitted)	-	-	-
E	- The "LF" products meet regulations as descr - The housing will whist 3.5 seconds in a wave	t european union Directives a ibed in GS-22-008. tand exposure to 260°C peak t solder application with a l.	emperature for .6mm minimum thick	TABLE I:PCB HOL			SIGNAL					E
	- Termination plating sy - Signal contacts: N - Power contacts: N - Active area plating sy	li + Gold I.27µmi+Sn 2.5 to 7.5µ,pure sec:		30 A 2.00 40 A 2.80 Max current 0 +0.	Ø 2.40 Ø 3.10	- Ø3.10	ØO.9 min			I 3W3 FOR EXAMPL	ion mm	_
Copyright 1	- Signal and power of - Shell plating :2 to - Accessories: Sn pu - Packaging spec: Se	4µm Cu + nickel + 3 to ∣0 µre bright + nickel	µmm Sn,pure bright	power ØA 0	PCB HOLE +/-0.1	PCB HOLE +/-0.1	PCB HOLE	dr         date           gr         2016         Eng         P         LEGARE           002         2006-10-11         Chr         Chr         Eng         P         LEGARE           002         2006-10-12         Chr         Chr         Eng         P         LEGARE           002         2006-10-12         Chr         Appr         F         Eng         P         LEGARE           SA         2009/09/16         F         F         Image: Same Same Same Same Same Same Same Same	2005-10-11         ANGULAR           2005-10-11         ANGULAR           2005-10-11         of ±22           Product fami           SUB FEMALE DMW EUROPE           mixed power right angled sco	is offermist specified 0.x ±0.3 size 0.xx ±0.3 size 0.xx ±0.05 ECN 1y - Spec r C0 -86. 0.1der - CUSTOMER	Scole 2 2:1 F09-0092 ef	F 009

ľ



PART NUMBER D*xWxS500A30LF D*LxWxS500A30LF D*OxWxS500A30LF D*VxWxS500A30LF D*xWxS500H30LF D*LxWxS500H30LF D*XxS500H30LF D*VxWxS500H30LF	AMPS 30 30 30 30 30 30 30 30 30	MATINGS/ UNMATINGS 200 200 200 200 200	FRONT ACCESSORY without insert M3 insert UNC 4.40	PCB ACCESSORIES without	shell size *	LAYOUTS						
D+L×W×S500A30LF D+O×W×S500A30LF D+V×W×S500A30LF D+V×W×S500H30LF D+L×W×S500H30LF D+O×W×S500H30LF D+V×W×S500H30LF	30 30 30 30 30 30	200 200 200 200	without insert M3		*	W/	PART NUMBER	AMPS	MATINGS/	FRONT	PCB	
D+L×W×S500A30LF D+O×W×S500A30LF D+V×W×S500A30LF D+V×W×S500H30LF D+L×W×S500H30LF D+O×W×S500H30LF D+V×W×S500H30LF	30 30 30 30 30 30	200 200 200	insert M3	wirnour		x W x	D*xWxS543A30LF	30	UNMATINGS 500	ACCESSORY without	ACCESSORIES without	
D+OxWxS500A30LF D+VxWxS500A30LF D+xWxS500H30LF D+LxWxS500H30LF D+OxWxS500H30LF D+VxWxS500H30LF	30 30 30 30 30	200 200		without	F	5WI	D*L xWx S543A30LF	30	500	insert M3		
D+VxWxS500A30LF D+xWxS500H30LF D+LxWxS500H30LF D+OxWxS500H30LF D+VxWxS500H30LF	30 30 30	200	THSELL ONC 4.40	without without	L		D*OxWxS543A30LF	30	500	insert UNC 4.40	without	
D • xWxS500H30LF D • L xWxS500H30LF D • O xWxS500H30LF D • V xWxS500H30LF	30 30		1 came 1 a		А	W	D*VxWxS543A30LF	30	500		without	
D*LxWxS500H30LF D*OxWxS500H30LF D*VxWxS500H30LF	30	200	female screw UNC 4.40	without	А	7W2	D*xWxS543H30LF	30		female screw UNC 4.40	without	
D∗Ox₩xS500H30LF D∗Vx₩xS500H30LF		200	without	metal bracket+harpoon PCB 2.40mm	7	1 11 2	D*LxWxS543H30LF	30	500	without	metal bracket+harpoon PCB 2.40mm	
D∗Vx₩xS500H30LF		200	insert M3 insert UNC 4.40	metal bracket+harpoon PCB 2.40mm metal bracket+harpoon PCB 2.40mm	В	2 I W I	D*OxWxS543H30LF	30	500	insert M3	metal bracket+harpoon PCB 2.40mm metal bracket+harpoon PCB 2.40mm	
	30			metal bracket+harpoon PCB 2.40mm	В	17W2	D*VxWxS543H30LF	30		insert UNC 4.40		
		200			D	I I W Z			500		metal bracket+harpoon PCB 2.40mm	
D*xWxS500G30LF	30	200	without	metal bracket+harpoon PCB 1.60mm	В	I 3W3	D*xWxS543G30LF	30	500	without	metal bracket+harpoon PCB 1.60mm	
D*LxWxS500G30LF	30	200	insert M3	metal bracket+harpoon PCB 1.60mm	D	OW A	D*LxWxS543G30LF	30	500	insert M3	metal bracket+harpoon PCB 1.60mm	
					U	J ⇒₩4						
					С	25W3						
					C	21.00.4						
					C	2 I W A 4						
					С	27W2						
*VXWXSSUUM3ULF	30	200	female screw UNC 4,40	metal bracket			D*VXWXS543M3ULF	30	500	female screw UNC 4,40	metal bracket	
		MATINGS	ERONT	PCB		I	[	1	MATINGS/	FRONT	PCB	
PART NUMBER	AMPS	UNMATINGS	ACCESSORY	ACCESSORIES			PART NUMBER	AMPS	UNMATINGS	ACCESSORY	ACCESSORIES	
D∗xWxS500A40LF	40	200	without	without			D*xWxS543A40LF	40	500	without	without	
D∗LxWxS500A40LF	40	200	insert M3	without			D*LxWxS543A40LF	40	500	insert M3	without	
D∗Ox₩xS500A40LF	40	200	insert UNC 4.40	without			D*OxWxS543A40LF	40	500	insert UNC 4.40	without	
D*VxWxS500A40LF	40	200	female screw UNC 4,40	without			D * V x W x S 5 4 3 A 4 0 L F	40	500	female screw UNC 4.40	without	
D∗xWxS500H40LF	40	200	without	metal bracket+harpoon PCB 2.40mm			D*xWxS543H40LF	40	500	without	metal bracket+harpoon PCB 2.40mm	
D∗L×W×S500H40LF	40	200	insert M3	metal bracket+harpoon PCB 2.40mm			D*LxWxS543H40LF	40	500	insert M3	metal bracket+harpoon PCB 2.40mm	
D∗OxWxS500H40LF	40	200	insect UNC 4 40	metal bracket+harpoon PCB 2.40mm				40	600	insert UNC 4.40	metal bracket+harpoon PCB 2.40mm	
			Linger Long 4.40				D*OxWxS543H40LF		500			
D∗VxWxS500H40LF	40	200		metal bracket+harpoon PCB 2.40mm			D*OxWxS543H40LF D*VxWxS543H40LF	40	500	female screw UNC 4.40	metal bracket+harpoon PCB 2.40mm	
D*VxWxS500H40LF D*xWxS500G40LF				metal bracket+harpoon PCB 2.40mm metal bracket+harpoon PCB 1.60mm						female screw UNC 4.40 without	metal bracket+harpoon PCB 2.40mm metal bracket+harpoon PCB 1.60mm	
	40	200	female screw UNC 4.40				D*VxWxS543H40LF	40	500			
D∗x₩x\$500G40LF	40 40	200	female screw UNC 4.40 without	metal bracket+harpoon PCB 1.60mm			D * V x W x S 5 4 3 H 4 0 L F D * x W x S 5 4 3 G 4 0 L F	40	500	without	metal bracket+harpoon PCB 1.60mm	
D*xWxS500G40LF D*LxWxS500G40LF	40 40 40	200 200 200	female screw UNC 4.40 without insert M3 insert UNC 4.40	metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm			D * V x W x S 5 4 3 H 4 0 L F D * x W x S 5 4 3 G 4 0 L F D * L x W x S 5 4 3 G 4 0 L F	40 40 40	500 500 500	without insert M3 insert UNC 4.40	metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm	
D*xWxS500G40LF D*LxWxS500G40LF D*OxWxS500G40LF	40 40 40 40	200 200 200 200	female screw UNC 4.40 without insert M3 insert UNC 4.40	metal bracket+harpoon PCB I.60mm metal bracket+harpoon PCB I.60mm metal bracket+harpoon PCB I.60mm			D * V x W x S 5 4 3 H 4 0 L F D * x W x S 5 4 3 G 4 0 L F D * L x W x S 5 4 3 G 4 0 L F D * O x W x S 5 4 3 G 4 0 L F	40 40 40 40	500 500 500 500	without insert M3 insert UNC 4.40	metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm	
D * x W x S 500G 40L F D * L x W x S 500G 40L F D * 0 x W x S 500G 40L F D * V x W x S 500G 40L F	40 40 40 40 40 40	200 200 200 200 200	femole screw UNC 4.40 without insert M3 insert UNC 4.40 femole screw UNC 4.40	metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm			D • V x W x S 5 4 3 H 4 0 L F D * x W x S 5 4 3 G 4 0 L F D • L x W x S 5 4 3 G 4 0 L F D • O x W x S 5 4 3 G 4 0 L F D • O x W x S 5 4 3 G 4 0 L F	40 40 40 40 40 40	500 500 500 500 500	without insert M3 insert UNC 4.40 female screw UNC 4.40	metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm	
D*xWxS500G40LF D*LxWxS500G40LF D*OxWxS500G40LF D*VxWxS500G40LF D*xWxS500M40LF	40 40 40 40 40 40 40	200 200 200 200 200 200 200	femole screw UNC 4.40 without insert M3 insert UNC 4.40 femole screw UNC 4.40 without	metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket			D * V x W x S 5 4 3 H 4 0 L F D * x W x S 5 4 3 G 4 0 L F D * L x W x S 5 4 3 G 4 0 L F D * 0 x W x S 5 4 3 G 4 0 L F D * 0 x W x S 5 4 3 G 4 0 L F D * v x W x S 5 4 3 G 4 0 L F	40 40 40 40 40 40 40	500 500 500 500 500 500	without insert M3 insert UNC 4.40 female screw UNC 4.40 without	metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket+harpoon PCB 1.60mm metal bracket	
	xWxS500A40LF •LxWxS500A40LF •OxWxS500A40LF •VxWxS500A40LF •xWxS500H40LF •LxWxS500H40LF	VXWxS500G30LF         30           xxWxS500M30LF         30           vLxWxS500M30LF         30           vCxWxS500M30LF         30           vCxWxS500M30LF         30           vXxWxS500M30LF         30           vXxWxS500M30LF         30           vXxWxS500M30LF         40           vXxWxS500A40LF         40           vXxXS500A40LF         40           vXxXS500A40LF         40           vXxXS500A40LF         40           vXxXS500A40LF         40           vXxXS500A40LF         40	VXWxS500G30LF         30         200           xXwxS500M30LF         30         200           xLxWxS500M30LF         30         200           xVxWxS500M30LF         30         200           xVxWxS500A40LF         40         200           xVxWxS500A40LF         40         200           xVxWxS500A40LF         40         200           xWxS500A40LF         40         200           xWxS500A40LF         40         200           xWxS500A40LF         40         200	VXWxS500G30LF         30         200         femole screw UNC 4.40           xxWxS500M30LF         30         200         without           vLxWxS500M30LF         30         200         insert M3           v0xWxS500M30LF         30         200         insert M3           v0xWxS500M30LF         30         200         insert UNC 4.40           v0xWxS500M30LF         30         200         femole screw UNC 4.40           vVxWxS500M30LF         30         200         femole screw UNC 4.40           vVxWxS500A40LF         40         200         without           vLxWxS500A40LF         40         200         insert UNC 4.40           vVxWxS500A40LF         40         200         femole screw UNC 4.40           vXwxS500A40LF         40         200         insert UNC 4.40           vXwxS500A40LF         40         200         insert M3           vXwxS500A40LF         40         200         without           vXwxS500A40LF         40         200         without           vLwxS500H40LF         40         200         without	VXWxS500G30LF       30       200       female screw UNC 4.40       metal bracket+harpoon PCB 1.60mm         vXWxS500M30LF       30       200       without       metal bracket         vLxWxS500M30LF       30       200       insert M3       metal bracket         v0xWxS500M30LF       30       200       insert M3       metal bracket         v0xWxS500M30LF       30       200       insert M3       metal bracket         v0xWxS500M30LF       30       200       female screw UNC 4.40       metal bracket         vVxWxS500M30LF       30       200       female screw UNC 4.40       metal bracket         vVxWxS500A40LF       40       200       without       without         vLxWxS500A40LF       40       200       insert M3       without         vXwxS500A40LF       40       200       insert UNC 4.40       without         vXwxS500A40LF       40       200       insert M3       without         vXwxS500A40LF       40       200       insert M4       without         vXwxS500A40LF       40       200       without       without         vXwxS500A40LF       40       200       without       without         vXwxS500H40LF       40       200<	VXWxS500G30LF       30       200       female screw UNC 4.40       metal bracket+harpoon PCB 1.60mm       C         vxWxS500M30LF       30       200       without       metal bracket       C         vLxWxS500M30LF       30       200       insert M3       metal bracket       C         v0xWxS500M30LF       30       200       insert M3       metal bracket       C         v0xWxS500M30LF       30       200       insert UNC 4.40       metal bracket       C         v0xWxS500M30LF       30       200       insert UNC 4.40       metal bracket       C         v0xWxS500M30LF       30       200       female screw UNC 4.40       metal bracket       C         v1xWxS500A40LF       40       200       without       without       Without       C         v0xWxS500A40LF       40       200       insert M3       without       Without       Mithout         v1xWxS500A40LF       40       200       insert WC 4.40       without       Mithout       Mi	VXWXS500G30LF       30       200       female screw UNC 4.40       metal bracket+harpoon PCB 1.60mm         VXWXS500M30LF       30       200       without       metal bracket         VXWXS500M30LF       30       200       insert M3       metal bracket         VXWXS500M30LF       30       200       insert M3       metal bracket         VXWXS500M30LF       30       200       insert UNC 4.40       metal bracket         VXWXS500M30LF       30       200       female screw UNC 4.40       metal bracket         VXWXS500M30LF       30       200       female screw UNC 4.40       metal bracket       C       2 T W 2	VX WX S500G 30 LF30200female screw UNC 4.40metal bracket+harpoon PCB 1.60mmC2 5W 3VX WX S500M 30 LF30200insert M3metal bracketC2 1 WA 4VX WX S500M 30 LF30200insert M0metal bracketC2 1 WA 4VX WX S500M 30 LF30200insert UNC 4.40metal bracketC2 7 W2VX WX S500M 30 LF30200female screw UNC 4.40metal bracketC2 7 W2PARTNUMBERAMPSMATINGS/ UNMATINGSFRONT ACCESSORYPCB ACCESSORIESPCB ACCESSORIESPARTNUMBERVX WX S500A40 LF40200insert UNC 4.40withoutwithoutD+L XW X5543A40 LFVX WX S500A40 LF40200insert UNC 4.40withoutD+V XW X5543A40 LFVX WX S500A40 LF40200female screw UNC 4.40withoutVX WX S500H40 LF40200withoutmetal bracket+harpoon PCB 2.40mmVX WX S500H40 LF40200insert M3metal bracket+harpoon PCB 2.40mmVX WX S500H40 LF40200insert M3metal bracket+harpoon PCB 2.40mm	VXWXSS00G30LF       30       200       female screw UNC 4.40       metal bracket       C       25W3         VXWXSS00M30LF       30       200       without       metal bracket       C       21WA4         VXWXSS00M30LF       30       200       insert M3       metal bracket       C       21WA4         VXWXSS00M30LF       30       200       insert M3       metal bracket       C       21WA4         VXWXSS00M30LF       30       200       insert M3       metal bracket       C       27W2       D+LxWxS543M30LF       30         VXWXS500M30LF       30       200       female screw UNC 4.40       metal bracket       C       27W2       D+LxWxS543M30LF       30         PART       NUMBER       AMPS       MATINGS/ UNMATINGS       FRONT ACCESSORY       PCB ACCESSORIES       C       27W2       PART       NUMBER       AMPS         VXWXS500A40LF       40       200       without       without       without       D+LxWxS543A40LF       40         VXWXS500A40LF       40       200       insert M3       without       metal bracket+horpoon PCB 2.40mm       D+LxWxS543H40LF       40         D*XWXS543H40LF       40       200       insert M3       metal bracket+horpoon PCB 2.40mm <td>VVXWxS500G30LF       30       200       femole screw UNC 4.40       metal bracket+horpoon PCB 1.60mm         VVXWxS500M30LF       30       200       without       metal bracket         VVXWxS500M30LF       30       200       insert M3       metal bracket         VVXWxS500M30LF       30       200       insert W1C 4.40       metal bracket         VXxWxS500A40LF       40       200       without       without       intert bracket         VXWxS500A40LF       40       200       without       without       without         vXxWxS500A40LF       40       200       insert W1C 4.40       without         vXwxS500A40LF       40       200       insert W2 4.40       without</td> <td>VX WX S500G30LF       30       200       female screw UNC 4.40       metal bracket harpoon PCB 1.60mm         VX WX S500M30LF       30       200       without       metal bracket       C       2 SW3         VX WX S500M30LF       30       200       insert M3       metal bracket       C       2 IWA 4         VX WX S500M30LF       30       200       insert M4       metal bracket       C       2 IWA 4         VX WX S500M30LF       30       200       insert M4       metal bracket       C       2 WX         VX WX S500M30LF       30       200       female screw UNC 4.40       metal bracket       C       2 WX       2 WX       D * XWX S543M30LF       30       500       insert M3         VX WX S500M30LF       30       200       female screw UNC 4.40       metal bracket       C       2 WX       2 WX       2 WX         VX WX S500A40LF       40       200       without       without       2 WX       2 WX       2 WX       2 WX       30       500       insert M3         VX WX S500A40LF       40       200       insert M3       without       Without       10 * WX S543A40LF       40       500       insert M3         VX WX S500A40LF       40       200</td> <td>VX XX S50030LF       30       200       female scree UNC 4.40       metal bracket horpoon PCB 1.60m         VX XX S50030LF       30       200       without       metal bracket       C       25W3         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket horpoon PCB 1.60m         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       40       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50040LF       40       200       without       without       metal bracket       C       21WA 543A0LF       40       500       insert UNC 4.40       without         VX XX S500A40LF       40       200       insert UNC 4.40</td>	VVXWxS500G30LF       30       200       femole screw UNC 4.40       metal bracket+horpoon PCB 1.60mm         VVXWxS500M30LF       30       200       without       metal bracket         VVXWxS500M30LF       30       200       insert M3       metal bracket         VVXWxS500M30LF       30       200       insert W1C 4.40       metal bracket         VXxWxS500A40LF       40       200       without       without       intert bracket         VXWxS500A40LF       40       200       without       without       without         vXxWxS500A40LF       40       200       insert W1C 4.40       without         vXwxS500A40LF       40       200       insert W2 4.40       without	VX WX S500G30LF       30       200       female screw UNC 4.40       metal bracket harpoon PCB 1.60mm         VX WX S500M30LF       30       200       without       metal bracket       C       2 SW3         VX WX S500M30LF       30       200       insert M3       metal bracket       C       2 IWA 4         VX WX S500M30LF       30       200       insert M4       metal bracket       C       2 IWA 4         VX WX S500M30LF       30       200       insert M4       metal bracket       C       2 WX         VX WX S500M30LF       30       200       female screw UNC 4.40       metal bracket       C       2 WX       2 WX       D * XWX S543M30LF       30       500       insert M3         VX WX S500M30LF       30       200       female screw UNC 4.40       metal bracket       C       2 WX       2 WX       2 WX         VX WX S500A40LF       40       200       without       without       2 WX       2 WX       2 WX       2 WX       30       500       insert M3         VX WX S500A40LF       40       200       insert M3       without       Without       10 * WX S543A40LF       40       500       insert M3         VX WX S500A40LF       40       200	VX XX S50030LF       30       200       female scree UNC 4.40       metal bracket horpoon PCB 1.60m         VX XX S50030LF       30       200       without       metal bracket       C       25W3         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket horpoon PCB 1.60m         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       30       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50030LF       40       200       insert UNC 4.40       metal bracket       C       21WA 4         VX XX S50040LF       40       200       without       without       metal bracket       C       21WA 543A0LF       40       500       insert UNC 4.40       without         VX XX S500A40LF       40       200       insert UNC 4.40

