Effective July 2017 Supersedes March 2007

LDS0705 Shielded metalized drum core power inductors



Applications

- Buck or Boost Inductor
- Noise filtering and output filter chokes
- Battery Power, DC-DC converters
- Notebook and laptop power
- Hand held devices
- Media players

Environmental data

- Storage temperature range (component): 40 °C to +125 °C
- Operating temperature range: -40 °C to +125 °C (ambient plus self-temperature rise)
- Solder reflow temperature: J-STD-020 (latest revision) compliant





Product specifications

Part Number	Rated Inductance (µH)	OCL (1) μΗ	Irms(2) (A)	lsat (3) (A)	DCR (Ω) @+20 °C (Typical)	K-factor (4)
LDS0705-R82M-R	0.82	0.861±20%	7.68	8.57	0.0040	24.8
LDS0705-1R5M-R	1.5	1.42±20%	6.17	6.67	0.0061	19.3
LDS0705-2R2M-R	2.2	2.13±20%	5.06	5.45	0.009	15.8
LDS0705-3R3M-R	3.3	2.97±20%	4.19	4.62	0.013	13.4
LDS0705-4R7M-R	4.7	5.08±20%	3.32	3.53	0.021	10.2
LDS0705-6R8M-R	6.8	6.34±20%	3.11	3.16	0.024	9.2
LDS0705-8R2M-R	8.2	7.75±20%	2.67	2.86	0.033	8.3
LDS0705-100M-R	10.0	9.30±20%	2.54	2.61	0.036	7.6
LDS0705-150M-R	15.0	14.78±20%	2.04	2.07	0.056	6.0
LDS0705-220M-R	22.0	21.53±20%	1.66	1.71	0.084	5.0
LDS0705-330M-R	33.0	32.50±20%	1.48	1.40	0.107	4.0
LDS0705-470M-R	47.0	45.71±20%	1.21	1.18	0.158	3.4
LDS0705-680M-R	68.0	69.76±20%	0.985	0.952	0.240	2.8
LDS0705-820M-R	82.0	83.67±20%	0.850	0.870	0.323	2.5
LDS0705-101M-R	100.0	98.9±20%	0.808	0.800	0.357	2.3
LDS0705-151M-R	150.0	152.0±20%	0.649	0.045	0.554	1.9
LDS0705-221M-R	220.0	216.5±20%	0.584	0.541	0.68	1.6
LDS0705-331M-R	330.0	329.9±20%	0.470	0.438	1.06	1.3
LDS0705-471M-R	470.0	467.0±20%	0.387	0.368	1.56	1.1

(1) Open Circuit Inductance Test Parameters: 100 kHz, 0.1 V, 0.0 Adc.


(2) Irms: DC current for an approximate ∆T of 30 °C without core loss. Derating is necessary for AC currents. PCB layout, trace thickness and width, air-flow, and proximity of other heat generating components will affect the temperature rise. It is recommended that the temperature of the part not exceed +125 °C under worst case operating conditions verified in the end application. (4) K-factor: Used to determine B p-p for core loss (see graph). B p-p = K*L*Δ, B p-p(mT), K: (K factor from table), L: (Inductance in μH), Δ(Peak to peak ripple current in Amps).

(5) Part Number Definition: LDS0705-xxx-R

LDS0705 = Product orde and size; -xxx = Inductance value in uH; P = decirnal point; If no R is present, last character equals number of zeros. M = Inductance to lerar ce +/- 20% -P suffix = RoHS compliant


(3) Isat Amperes peak for approximately 15% rolloff (@+25 °C) M = Inductance to eran

Dimensions- mm




Marking: xxx = Inductance in t.H. P = decimal point. If no P is present last character equals number of zeros, ww.lyy = Date code, R = R evision level. Do not route traces or vias underneath the inductor

Packaging information- mm




LDS0705 Shielded metalized drum core power inductors

Temperature rise vs. total loss



Solder Reflow Profile



Reference JDEC J-STD-020

Profile Feature	460	Standard SnPb Solder	Lead (Pb) Free Solder
Preheat and Soak	• Temperature min. (T _{smin})	100°C	150°C
	• Temperature max. (T _{smax})	150°C	200°C
	• Time (T _{smin} to T _{smax}) (t _s)	60-120 Seconds	60-120 Seconds
Average ramp up rat	e T _{smax} to Tp	3°C/ Second Max.	3°C/ Second Max.
Liquidous temperatu	re (IL)	183°C	217°C
Time at liquidous (t _L)		60-150 Seconds	60-150 Seconds
Peak package body	emperature (T _P)*	Table 1	Table 2
	$^{\circ}$ C of the specified classification temperature (1.)	20 Seconds**	30 Seconds**
Average ramp-down	rate (Tp to Tsmax)	6°C/ Second Max.	6°C/ Second Max.
Time 25°C to Peak T	emperature	6 Minutes Max.	8 Minutes Max.

* Tolerance for peak profile temperature (T_p) is defined as a supplier minimum and a user maximum.

** Tolerance for time at peak profile temperature (t_p) is defined as a supplier minimum and a user maximum.

Life Support Policy: Eaton does not authorize the use of any of its products for use in life support devices or systems without the express written approval of an officer of the Company. Life support systems are devices which support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.

Eaton reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Eaton also reserves the right to change or update, without notice, any technical information contained in this bulletin.

Eaton Electronics Division 1000 Eaton Boulevard Cleveland, OH 44122 United States

, AI

www.eaton.com/electronics © 2017 Eaton All Rights Reserved Printed in USA

Publication No. 4142 July 2017

Powerina Business Worldwide

Eaton is a registered trademark.

All other trademarks are property of their respective owners.